8

Throughbeam photoelectric laser sensors

LSRL 8



en 06-2014/07 50126807

A²LS

- Red light laser in laser class 2 A²LS - Active Ambient Light Suppression •
- Adjustable focus
- M12 turning connector or cable connection
- Activation input





Accessories:

- (available separately)
- M12 connectors (KD ...)
- Ready-made cables (K-D ...)
- Mounting systems
- Diaphragms
- Control guard

Receiver

Α

- В Transmitter
- С Optical axis
- D Operational control
- Е Yellow LED
- Turning connector, 90° rot. angle F

Electrical connection

Dimensioned drawing

LSERL 8/24.01 LSERL 8/24.01-S12 br/BN 10-30VDC+ <u>ws/W</u>H 2. bl/BU GND sw/BK O₹ NC





LSSRL	8.9			
LSSRL	8.9-S12			
-	10-3	SOVDC+	-1	br/BN ws/WH bl/BU sw/BK
		NC	-2	ws/WH
		CND		bi/BU
		UND		sw/BK
		NU	-4	

NC	
LSSRL 8.98-S12 10-30VDC+ NC GND active NC	- 1

NC -5 In der Braike 1 D-73277 Owen Tel. +49 (0) 7021 573-0

LSRL 8/24.91... - 06 LSRL 8/44.98-S12 - 06

Leuze electronic

LSRL 8

60

with pin diaphragm in front of receiver

with slit diaphragm in front of receiver $\frac{1}{1}$.

16 20

100

Tables

without diaphragm:

8 10

Operating range [m] *

Typ. operating range limit [m] **

0

0

0



for focus adjusted to 2m for focus adjusted to ∞ * ** 1) Smallest object over the entire operating range with pin diaphragm: Ø=0.7mm, slit diaphragm: Ø=1.0mm

Diagrams



- Focus set to 0.125 m
- R Focus set to 2m
- С Focus set to 16 m

Specifications

Optical data

Typ. operating range limit 1) Operating range 2 Light spot diameter Focus adjustment range Beam divergence Light source Wavelength

Timing

Switching frequency Response time Delay before start-up

Electrical data

Operating voltage U_B ³⁾ Residual ripple Open-circuit current Switching output

Signal voltage high/low Output current Sensitivity

Indicators

Yellow LED, receiver Yellow LED flashing, receiver

Mechanical data

Housing Optics cover Weight (plug/cable) Connection type

Environmental data

Ambient temp. (operation/storage) Protective circuit ⁴⁾ VDE safety class 5) Degree of protection ⁶⁾ Laser class Standards applied Certifications

Options

Activation input active Transmitter active/not active

1) Typ. operating range limit: max. attainable range without performance reserve with focus set to ∞

.../24...

.../44...

- 2) Operating range: recommended range with performance reserve with focus set to 2m
- 3) For UL applications: for use in class 2 circuits according to NEC only 2=polarity reversal protection, 3=short circuit protection for all outputs 4Ì

Rating voltage 250VAC 5)

In end position of the turning connector (turning connector engaged) 6

7) IP 69K test acc. to DIN 40050 part 9 simulated, high pressure cleaning conditions without the use of additives, acids and bases are not part of the test

U_B/0V or not connected

2.3

These proximity switches shall be used with UL Listed Cable assemblies rated 30V, 0.5A min, 8) in the field installation, or equivalent (categories: CYJV/CYJV7 or PVVA/PVVA7)

Order guide

	Designation	Part no.
With M12 connector		
Transmitter and receiver	LSRL 8/24.91-S12	
Transmitter	LSSRL 8.9-S12	50036358
Receiver	LSERL 8/24.01-S12	50036359
With M12 connector		
Transmitter and receiver	LSRL 8/44.98-S12	
Transmitter	LSSRL 8.98-S12	50126800
Receiver	LSERL 8/44.01-S12	50126801
With 2m cable		
Transmitter and receiver	LSRL 8/24.91	
Transmitter	LSSRL 8.9	50037083
Receiver	LSERL 8/24.01	50037084

Remarks

intended use!

Operate in accordance with

♦ This product is not a safety sensor and is not intended as personnel protection. She product may only be put into operation by competent persons.
Only use the product in accordance with the intended use.

LSRL 8

Throughbeam photoelectric laser sensors

Laser safety notices

ATTENTION, LASER RADIATION - LASER CLASS 2

Never look directly into the beam!

The device fulfills the EN 60825-1:2008-05 (IEC 60825-1:2007) safety regulations for a product in **laser class 2** as well as the U.S. 21 CFR 1040.10 regulations with deviations corresponding to "Laser Notice No. 50" from June 24th, 2007.

- ♥ Never look directly into the laser beam or in the direction of reflecting laser beams!
- If you look into the beam path over a longer time period, there is a risk of injury to the retina.
- Do not point the laser beam of the device at persons!
- the laser beam with an opaque, non-reflective object if the laser beam is accidentally directed towards a person.
- rightarrow When mounting and aligning the device, avoid reflections of the laser beam off reflective surfaces!
- CAUTION! Use of controls or adjustments or performance of procedures other than specified herein may result in hazardous light exposure.
 - The use of optical instruments or devices (e.g., magnifying glasses, binoculars) with the product will increase eye hazard.
- Adhere to the applicable legal and local regulations regarding protection from laser beams acc. to EN 60825 (IEC 60825) in its latest version.
- ✤ The device must not be tampered with and must not be changed in any way. There are no user-serviceable parts inside the device. Repairs must only be performed by Leuze electronic GmbH + Co. KG.

NOTICE

Affix laser information and warning signs!

Laser information and warning signs are affixed to the device(see ①). In addition, self-adhesive laser information and warning signs (stick-on labels) are supplied in several languages (see ②).

- Affix the laser information sheet with the language appropriate for the place of use to the device.
- When using the device in the US, use the stick-on label with the "Complies with 21 CFR 1040.10" notice.
- Affix the laser information and warning signs near the device if no signs are attached to the device (e.g. because the device is too small) or if the attached laser information and warning signs are concealed due to the installation position. Affix the laser information and warning signs so that they are legible without exposing the reader to the laser radiation of the device or other optical radiation.



▲ Leuze electronic

LSRL 8