




Installation instructions
ExtendedController

ecomat100[®]

CR0133

UK



Contents

1	Preliminary note	4
1.1	Symbols used	4
1.2	Warning signs used	4
2	Safety instructions	5
2.1	General	5
2.2	Target group	5
2.3	Electrical connection	5
2.4	Housing temperature	5
2.5	Tampering with the device	6
2.6	Electromagnetic compatibility	6
2.7	Electrical welding on vehicles and plants	6
3	Functions and features	6
4	Installation	7
4.1	Fixing	7
4.2	Installation position	7
4.3	Mounting surface	8
4.4	Heat dissipation	8
5	Electrical connection	9
5.1	Wiring	9
5.1.1	Assignment of the connectors	9
5.2	Ground connection	9
5.3	Fuses	10
5.4	Laying the supply and signal cables	10
5.4.1	GND connections of the Ex connection side	11
5.5	Frequency and analogue inputs	11
5.6	Resistor inputs	11
5.6.1	Unused input I15	12
5.7	Supply low-side digital outputs (B_L)	12
5.8	CAN wiring St/Ex side	13
5.8.1	Point-to-point wiring	13
5.8.2	Open CANopen network	13
5.9	Connection technology	13
5.10	USB interface	14
5.10.1	Hardware requirement	14
5.10.2	Short-circuit protection	14
6	Set-up	15
6.1	Required documentation	15
6.2	Interfaces and system requirements	15
6.3	Programming via USB interface	15
6.3.1	Install the USB drivers	16
6.4	Uninstall the drivers	16

7	Technical data	17
7.1	Mechanical and electric data	17
7.2	Test standards and regulations	19
7.3	St side / Characteristics of the inputs	20
7.4	St side / Characteristics of the outputs	23
7.5	Ex side / Characteristics of the inputs	25
7.6	Ex side / Characteristics of the outputs	27
7.7	St side / Wiring	29
7.8	Ex side / Wiring	30
8	Maintenance, repair and disposal	31
9	Approvals / standards	31

1 Preliminary note

This document applies to devices of the type "ExtendedController" (art. no.: CR0133).



It is deemed as a part of the device.

This document is intended for specialists. These specialists are people who are qualified by their appropriate training and their experience to see risks and to avoid possible hazards that may be caused during operation or maintenance of the device. The document contains information about the correct handling of the device.

Read this document before use to familiarise yourself with operating conditions, installation and operation. Keep this document during the entire duration of use of the device.

Adhere to the safety instructions.

1.1 Symbols used

- ▶ Instruction
- > Reaction, result
- [...] Designation of pushbuttons, buttons or indications
- Cross-reference
-  Important note
Non-compliance can result in malfunction or interference.
-  Information
Supplementary note

1.2 Warning signs used

WARNING

Warning of serious personal injury.
Death or serious irreversible injuries may result.

CAUTION

Warning of personal injury.
Slight reversible injuries may result.

NOTE

Warning of damage to property.

2 Safety instructions

2.1 General

These instructions are part of the device. They contain information and illustrations about the correct handling of the device and must be read before installation or use.

Observe the operating instructions. Non-observance of the instructions, operation which is not in accordance with use as prescribed below, wrong installation or incorrect handling can seriously affect the safety of operators and machinery.

UK

2.2 Target group

These instructions are intended for authorised persons according to the EMC and low-voltage directives. The device must only be installed, connected and put into operation by a qualified electrician.

2.3 Electrical connection

Disconnect the device externally before handling it. If necessary, also disconnect any independently supplied output load circuits.

If the device is not supplied by the mobile on-board system (12/24 V battery operation), it must be ensured that the external voltage is generated and supplied according to the criteria for safety extra-low voltage (SELV) as this voltage is supplied without further measures to the connected controller, the sensors and the actuators.

The wiring of all signals in connection with the SELV circuit of the device must also comply with the SELV criteria (safety extra-low voltage, safe electrical isolation from other electric circuits).

If the supplied SELV voltage is externally grounded (SELV becomes PELV), the responsibility lies with the user and the respective national installation regulations must be complied with. All statements in this document refer to the device the SELV voltage of which is not grounded.

The connection terminals may only be supplied with the signals indicated in the technical data and/or on the device label and only the approved accessories of ifm electronic may be connected.

2.4 Housing temperature

According to the technical specifications below the device can be operated in a wide ambient temperature range. Because of the additional internal heating the housing walls can have high perceptible temperatures when touched in hot environments.

2.5 Tampering with the device

In case of malfunctions or uncertainties please contact the manufacturer. Tampering with the device can seriously affect the safety of operators and machinery. It is not permitted and leads to the exclusion of any liability and warranty claims.

2.6 Electromagnetic compatibility

This is a class A product. It can cause radio interference in domestic areas. In this case the operator is requested to take appropriate measures.

2.7 Electrical welding on vehicles and plants

Welding work on the chassis frame must only be carried out by qualified persons.

Remove and cover the plus and minus terminals of the batteries.

Disconnect all contacts of the controller from the on-board system prior to welding on the vehicle or plant. Connect the earth terminal of the welding device directly to the part to be welded.

Do not touch the controller or electric cables with the welding electrode or the earth terminal of the welding device.

Protect the controller against weld slag.

3 Functions and features

The freely programmable controllers of the "ExtendedController" series are rated for use under difficult conditions (e.g. extended temperature range, strong vibration, intensive EMC interference).

They are suited for direct installation in machines in mobile and robust applications. Integrated hardware and software functions (operating system) offer high protection for the machine.

The controllers can be used as CANopen master.

WARNING

The "ExtendedController" series is not approved for safety tasks in the field of safety of persons.

WARNING

The user is responsible for the safe function of the application programs which he created himself. If necessary, he must additionally carry out an approval test by corresponding supervisory and test organisations according to the national regulations.

4 Installation

4.1 Fixing


- ▶ Fix the controller to a flat surface using 4 M5 screws.
Screw material: steel or stainless steel
Tightening torque: 8 ± 2 Nm
- ▶ Connect the housing to GND (→ 5.2 Ground connection)

NOTE

Use screws with a low head to avoid that the connector is damaged when placed and locked.

UK


Screws to be used (examples)	Standard
Button head hexagon socket screws (M5 x L)	ISO 7380
Cylinder screws with hexagon socket and low head (M5 x L)	DIN 7984
Cutting screws for metric ISO thread with low head	DIN 7500



Example button head hexagon socket screw

4.2 Installation position

- ▶ Align the controller so that the cable entries of the connectors face downwards.




Preferred installation position

4.3 Mounting surface

NOTE

The housing must not be exposed to any torsional forces or mechanical stress.


- Use compensating elements if there is no flat mounting surface available.



Mounting surface

4.4 Heat dissipation

- Ensure sufficient heat dissipation as the internal heating of the electronics is conducted away via the housing.
- In case of sandwich mounting of controllers use spacers.



Heat dissipation and sandwich mounting

5 Electrical connection

5.1 Wiring

Wiring (→ 7 Technical data)




Only connect the connector pins as shown in the pin layout.
Unspecified connector pins remain unconnected.

- Connect all indicated supply cables and GND terminals (St and Ex connection side).

5.1.1 Assignment of the connectors

- Note the device label.



Assignment of the connectors on the device label

NOTE

Inversion of the connectors can lead to damage to the reference voltage output (pin 51, controller side).


NOTE

Inversion of the connectors can lead to damage to a connected PC or notebook.

5.2 Ground connection



To ensure the protection of the device against electrical interference and the safe function of the device, the housing must be connected to the ground of the vehicle.



1: Drill holes for ground connection


- Establish a connection between the device and the ground of the vehicle using M5 screws.
Screws to be used (→ 4.1 Fixing)

5.3 Fuses

- The individual electric circuits must be protected in order to protect the whole system.

Connection side	Description	Potential	Pin no.	Fuse
St (Standard)	Supply voltage sensors/module	VBB_s	St-10	$\leq 2\text{ A T}$
	Supply voltage outputs	VBB_o	St-19	$\leq 15\text{ A}$
	Supply voltage via relay	VBB_R	St-01	$\leq 15\text{ A}$
Ex (Extended)	Supply voltage sensors/module	VBB_s	Ex-10	$\leq 2\text{ A T}$
	Supply voltage output group 1	VBB_1	Ex-19	$\leq 15\text{ A}$
	Supply voltage output group 2	VBB_2	Ex-01	$\leq 15\text{ A}$

5.4 Laying the supply and signal cables



Example St connection side (X = not permissible)

⚠ WARNING

The linking of connections in the plug is not permitted and can affect the safety of operators and machinery.

- Basically all supply and signal cables must be laid separately.
- Screen signal cables in EMC critical applications.
- Connect supply and ground cables to the controller and the sensors/actuators via the respective common star point.



If a prewired connection cable is used, remove the cores with unused signal inputs and outputs.

Unused cores, in particular core loops, lead to interference coupling that can influence the connected controller.


5.4.1 GND connections of the Ex connection side

- Connect all GND connections of the Ex connection side to the common GND star point.

5.5 Frequency and analogue inputs

- Operate inputs with screened cables, so that useful signals are not affected by external interference.
- Connect screens to ground on one side.

5.6 Resistor inputs



Ground return resistor inputs


- Equip each resistor with an own, separated ground return to ensure measurement accuracy.

5.6.1 Unused input I15



If the input I15 is not used it must be configured as digital input.

5.7 Supply low-side digital outputs (B_L)




Supply low-side digital outputs (B_L)

- 1: Outputs of the output group VBB_O
- 2: Outputs of the output group VBB_R

► Note the potential allocation of the outputs.
The supply of an output within an output group must only be carried out via the corresponding, protected potential.


5.8 CAN wiring St/Ex side

5.8.1 Point-to-point wiring



1. Extended side: CAN2 (with factory pre-configuration)
2. Standard side: CANn (interface selectable)
3. Terminating CAN resistor in the cable

5.8.2 Open CANopen network



1. Extended side: CAN2 (with factory pre-configuration)
2. Standard side: CANn (interface selectable)
3. Terminating CAN resistors

5.9 Connection technology


NOTE

Only connect the 55-pole connectors when the supply voltage is disconnected.
No "hot plugging" is permitted.

5.10 USB interface

5.10.1 Hardware requirement

The USB controller used is USB 2.0 compatible. The USB interface is provided as a virtual COM port under Windows (→ 6.3 Programming via USB interface).



1. Controller (2 x 55-pole connector; USB port on St side)
2. USB connector for programming and service purposes
3. Notebook/PC

- A** Connection controller to USB connector, permanent (≤ 3 m).
- ▶ Position the USB connector in immediate vicinity to the controller. The cable length "A" considerably influences the quality of the USB data transmission.
- B** Connection USB connector to notebook / PC, temporary
- ▶ Use a connection cable with the designation "Full Speed/High Speed" (= USB connection cable with twisted and screened cores).
 - ▶ Do not make a connection using several USB connection cables.
 - ▶ Remove the connection cable after the programming or service works.

5.10.2 Short-circuit protection

NOTE

The USB interface is not protected against short circuits with a live wire outside the following voltage ranges:

USB_P: -0.5...3.8 V DC

USB_N: -0.5...3.8 V DC

USB_5V: -0.5...10.0 V DC

A short circuit will destruct the USB interface.

6 Set-up



On delivery the extended side is pre-configured as CANopen slave. However, the user can also program the extended side freely.

6.1 Required documentation

The user can easily create the application program by means of the IEC 61131-3 compliant programming system CODESYS 2.3. In addition to the programming system CODESYS, the following documents are required for programming and commissioning of the controller:

- System manual CR0133
(alternatively CODESYS 2.3 online help)
- Manual on PLC programming with CODESYS 2.3
(alternatively CODESYS 2.3 online help)

The system manual CR0133 is available for download on the internet:
www.ifm.com → Data sheet search → CR0133 → Operating instructions

The manual on PLC programming with CODESYS 2.3 and the online help are automatically installed on the PC upon installation of the CODESYS package from the *ecomatmobile* DVD.

As an alternative, the CODESYS package can be downloaded from the internet:
www.ifm.com → Service → Download → Systems for mobile machines*

*) Download area with registration

6.2 Interfaces and system requirements



System requirement for RS-232 and CAN:
Microsoft Windows XP SP1 or higher

System requirement for USB:
Microsoft Windows XP SP2, Windows 7

6.3 Programming via USB interface



Note in general:

- The controller can be connected to any USB interface. The number of the COM port does not change.
- Only connect one controller for programming to the PC.
- Special USB and COM port drivers are required.

6.3.1 Install the USB drivers

The driver provides a "virtual COM port", i.e. another artificial serial interface, on the PC.

The driver file "USB CR0032 setup vxxxx.exe" is made available on the *ecomatmobile* DVD.

As an alternative, the driver is also available on the internet.

www.ifm.com → Service → Download → Systems for mobile machines*

*) Download area with registration



Changes to the system settings of the PC require extended user rights. Contact your system administrator.



Installation under Windows 7 will be described in the following. In other Windows versions there may be different menu names or structures.

- ▶ Start the driver file "USB CR0032 setup vxxxx.exe" and follow the setup instructions.
- > The driver files and a documentation will be copied to the following directory:
C:\Program Files (x86)\ifm electronic\USB_Driver_R360.
- ▶ Reboot the PC.
- ▶ Connect the controller to a free USB port
- ▶ Carry out the driver installation according to the "Installation_Guide".
The document "Installation_Guide.pdf" can be found in the following directory:
C:\Program Files (x86)\ifm electronic\USB_Driver_R360\WHQL_Certified_Driver\Documentation\Installation_Guide.pdf

The driver to be installed can be found in the following directory:

C:\Program Files (x86)\ifm electronic\USB_Driver_R360\WHQL_Certified_Driver\

6.4 Uninstall the drivers



If a driver is to be updated, the installed drivers have to be uninstalled first.


- ▶ Uninstall the drivers according to the "Installation_Guide" (chapter 4).
The document "Installation_Guide.pdf" can be found in the following directory:
C:\Program Files (x86)\ifm electronic\USB_Driver_R360\WHQL_Certified_Driver\Documentation\Installation_Guide.pdf

7 Technical data

7.1 Mechanical and electric data

CR0133

Mobile controller
ExtendedController
32-bit processor
32 inputs
32 outputs
5 CAN interfaces
CODESYS 2.3
8...32 V DC



UK

Technical data

Mechanical data

Housing

Dimensions (H x W x D)

Installation

Connection

Weight

Housing/storage temperature

Protection rating

Electrical data

Input / output channels (total)

Inputs

Outputs

Operating voltage

Switch-on voltage

Overvoltage

Undervoltage detection

Undervoltage shutdown

Undervoltage detection

Undervoltage shutdown

Reverse polarity protection

Current consumption

CAN interfaces 1...5

Baud rate

Communication profile

Note

Controller as black-box system to implement a central or decentralised system design

closed, screened metal housing with flange fastening

153 x 247.5 x 43 mm

screw connection by means of 4 M5 x L screws to DIN 7500 or DIN 7984
mounting position horizontal or vertical to the mounting wall

2 55-pin connectors, latched, protected against reverse polarity, type AMP or Framatome
AMP junior timer contacts, crimp connection 0.5/2.5 mm²

1.6 kg

- 40...85 °C (depending on the load) / - 40...85 °C

IP 67 (for inserted connector with individually sealed cores, e.g. EC2084)

64 (32 inputs / 32 outputs)

configurable
digital for positive/negative sensor signals, positive with diagnostic capabilities
analogue (0...10/32 V, 0...20 mA, ratiometric)
frequency (≤ 30 kHz)
resistance measurement (3... 690 Ω , 0.016...30 k Ω ,)

configurable
digital positive/negative switching (high/low side)
analogue (0.02...10 V)
PWM output (20...250 Hz), current-controlled

8...32 V DC

> 10 V DC

≤ 36 V for $t \leq 10$ s

for $7.5 \text{ V} \leq U_B \leq 8 \text{ V}$
for $7.1 \text{ V} \leq U_B < 7.5 \text{ V}$ for $t \geq 100$ ms
(depending on the software)

for $U_B \leq 7.8 \text{ V}$
for $6.8 \text{ V} \leq U_B \leq 7.5 \text{ V}$

yes

≤ 210 mA (without external load at 24 V DC)

CAN interface 2.0 A/B, ISO 11898
50 Kbits/s...1 Mbit/s (default 125 Kbits/s)
CANopen, CiA DS 301 V4.01, CiA DS 306 V1.3
or SAE J 1939 or free protocol

If not otherwise specified, the data apply to the St and Ex side.

CR0133	
Serial interface	
Baud rate	
Topology	
Protocol	
Virtual COM port	
Processor	
Device monitoring	
Process monitoring concept	St
Physical memory	
Software/programming	
Programming system	
Indicators	
Status LED	St
	Ex
Operating states	St
No longer valid if the colours and/or flashing modes are changed by the application program.	
	Ex
Note	

Technical data		
RS-232 C		
9.6...115.2 kBit/s (default 115.2 kbits/s)		
point-to-point (max. 2 participants); master-slave connection		
predefined ifm protocol (INTELHEX)		
USB, max. 1 MBaud		
32-bit CPU Infineon TriCore 1796		
undervoltage monitoring		
watchdog function		
checksum test for program and system		
excess temperature monitoring		
Second switch-off mode for 8 outputs each via a relay		
flash: 2 Mbytes		
RAM: 2 Mbytes		
remanent memory: 64 Kbytes		
CODESYS version 2.3 (IEC 61131-3)		
three-colour LED (R/G/B)		
LED red / LED green		

7.2 Test standards and regulations

CR0133	Technical data	
Test standards and regulations		
CE marking	EN 61000-6-2: 2005	Electromagnetic compatibility (EMC) Noise immunity
	EN 61000-6-4: 2007	Electromagnetic compatibility (EMC) Emission standard
E1 marking	UN/ECE-R10	Emission standard Immunity with 100 V/m
Electrical tests	ISO 7637-2: 2004	Pulse 1, severity level: IV; function state C Pulse 2a, severity level: IV; function state A Pulse 2b, severity level: IV; function state C Pulse 3a, severity level: IV; function state A Pulse 3b, severity level: IV; function state A Pulse 4, severity level: IV; function state A Pulse 5, severity level: III; function state C (data valid for the 24 V system) Pulse 4, severity level: III; function state C (data valid for the 12 V system)
Climatic tests	EN 60068-2-30: 2006	Damp heat, cyclic upper temperature 55°C, number of cycles: 6
	EN 60068-2-78: 2002	Damp heat, steady state test temperature 40°C / 93% RH, Test duration: 21 days
	EN 60068-2-52: 1996	Salt spray test severity level 3 (motor vehicle)
Mechanical tests	ISO 16750-3: 2007	Test VII; Vibration, random mounting location: vehicle body
	EN 60068-2-6: 2008	Vibration, sinusoidal 10...500 Hz; 0.72 mm/10 g; 10 cycles/axis
	ISO 16750-3: 2007	Bumps 30 g/6 ms; 24,000 shocks
Tests for railway applications	EN 50155-12-2: 2007	Electronic equipment used on rolling stock

UK

7.3 St side / Characteristics of the inputs

CR0133	St side / Characteristics of the inputs												
I00...07 Multifunction inputs with supply voltage independent levels for frequency measurement	<table> <tr> <td>Resolution</td><td>12 bits</td></tr> <tr> <td>Accuracy</td><td>$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)</td></tr> <tr> <td>Measuring ranges</td><td>0...10 V, 0...32 V, 0...20 mA, ratiometric</td></tr> </table>	Resolution	12 bits	Accuracy	$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)	Measuring ranges	0...10 V, 0...32 V, 0...20 mA, ratiometric						
Resolution	12 bits												
Accuracy	$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)												
Measuring ranges	0...10 V, 0...32 V, 0...20 mA, ratiometric												
Current input 0...20 mA (A)	<table> <tr> <td>Input resistance</td><td>390 Ω</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	390 Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	390 Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Voltage input 0...10 V (A)	<table> <tr> <td>Input resistance</td><td>65.6 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	65.6 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	65.6 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Voltage input 0...32 V (A)	<table> <tr> <td>Input resistance</td><td>50.7 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	50.7 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	50.7 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Voltage input ratiometric (A)	<table> <tr> <td>Input resistance</td><td>50.7 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	50.7 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	50.7 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Frequency input (FRQ)	<table> <tr> <td>Input resistance</td><td>3.2 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 30 kHz</td></tr> <tr> <td>Switch-on level</td><td>$> 0.35...0.55 U_B$</td></tr> <tr> <td>Switch-off level</td><td>$< 0.29 U_B$</td></tr> </table>	Input resistance	3.2 k Ω	Input frequency	≤ 30 kHz	Switch-on level	$> 0.35...0.55 U_B$	Switch-off level	$< 0.29 U_B$				
Input resistance	3.2 k Ω												
Input frequency	≤ 30 kHz												
Switch-on level	$> 0.35...0.55 U_B$												
Switch-off level	$< 0.29 U_B$												
Digital input (B _{LH})	<table> <tr> <td>Input resistance</td><td>3.2 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> <tr> <td>Switch-on level</td><td>$> 0.7 U_B$</td></tr> <tr> <td>Switch-off level</td><td>$< 0.3 U_B$</td></tr> <tr> <td>Diagnostics Short circuit to VBB</td><td>$> 0.95 U_B$</td></tr> <tr> <td>Diagnostics Short circuit to GND / wire break</td><td>< 1 V</td></tr> </table>	Input resistance	3.2 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)	Switch-on level	$> 0.7 U_B$	Switch-off level	$< 0.3 U_B$	Diagnostics Short circuit to VBB	$> 0.95 U_B$	Diagnostics Short circuit to GND / wire break	< 1 V
Input resistance	3.2 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Switch-on level	$> 0.7 U_B$												
Switch-off level	$< 0.3 U_B$												
Diagnostics Short circuit to VBB	$> 0.95 U_B$												
Diagnostics Short circuit to GND / wire break	< 1 V												
I08...11 Multifunction inputs with fixed levels for frequency measurement	<table> <tr> <td>Resolution</td><td>12 bits</td></tr> <tr> <td>Accuracy</td><td>$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)</td></tr> <tr> <td>Measuring ranges</td><td>0...10 V, 0...32 V, 0...20 mA, ratiometric</td></tr> </table>	Resolution	12 bits	Accuracy	$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)	Measuring ranges	0...10 V, 0...32 V, 0...20 mA, ratiometric						
Resolution	12 bits												
Accuracy	$\pm 1\%$ FS (in the measuring range 0...20 mA: $\pm 2\%$ FS)												
Measuring ranges	0...10 V, 0...32 V, 0...20 mA, ratiometric												
Current input 0...20 mA (A)	<table> <tr> <td>Input resistance</td><td>390 Ω</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	390 Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	390 Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Voltage input 0...10 V (A)	<table> <tr> <td>Input resistance</td><td>65.6 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	65.6 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	65.6 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												
Voltage input 0...32 V (A)	<table> <tr> <td>Input resistance</td><td>50.7 kΩ</td></tr> <tr> <td>Input frequency</td><td>≤ 1 kHz (default 35 Hz)</td></tr> </table>	Input resistance	50.7 k Ω	Input frequency	≤ 1 kHz (default 35 Hz)								
Input resistance	50.7 k Ω												
Input frequency	≤ 1 kHz (default 35 Hz)												

CR0133

Voltage input ratiometric (A)

Frequency input (FRQ*)

Digital input (B_i)**I12...14
Digital / resistor inputs**Digital input (B_i)

Resistor input (R)

St side / Characteristics of the inputs

Input resistance	50.7 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)

Input resistance	3.2 kΩ / 50.7 kΩ in case of corresponding parameter setting
Input frequency	≤ 30 kHz
Switch-on level	> 4 V
Switch-off level	< 2 V

Input resistance	3.2 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	> 0.7 U _B
Switch-off level	< 0.3 U _B
Diagnostics Short circuit to VBB	> 0.95 U _B
Diagnostics Short circuit to GND / wire break	< 1 V

Resolution	12 bits
------------	---------

Input resistance	3.2 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	> 0.7 U _B
Switch-off level	< 0.3 U _B
Diagnostics Short circuit to VBB	> 0.95 U _B
Diagnostics Short circuit to GND / wire break	< 1 V
Voltage on the pin when not connected	≤ 0.2 V

Measuring current	< 2.0 mA
Input frequency	50 Hz
Measuring range	16 Ω...30 kΩ
Accuracy	± 2% FS: 16 Ω...3 kΩ ± 5% FS: 3...15 kΩ ± 10% FS: 15...30 kΩ
Diagnostics Short circuit to VBB	> 31 kΩ

UK

CR0133**I15
Digital / resistor input**Digital input (B_L)

Resistor input (R)

Note

Test input (pin 50)

Abbreviations**St side / Characteristics of the inputs**

Resolution	12 bits
------------	---------

Input resistance	3.2 k Ω
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	$> 0.7 U_B$
Switch-off level	$< 0.3 U_B$
Diagnostics Short circuit to VBB	$> 0.95 U_B$
Diagnostics Short circuit to GND / wire break	< 1 V
Voltage on the pin when not connected	≤ 0.2 V

Measuring current	< 5.0 mA
Input frequency	50 Hz
Measuring range	3...680 Ω
Accuracy	± 4 % FS
Diagnostics Short circuit to VBB / wire break	> 700 Ω

During the test mode (e.g. programming) the connector pin must be connected to VBB_s (8...32 V DC).
During the "RUN" mode the test input must not be connected.

A	Analogue
B _H	Binary high side
B _L	Binary low side
FRQ	Frequency / pulse inputs with levels depending on the supply voltage
FRQ*	Frequency / pulse inputs with fixed levels
H	H-bridge function
PWM	Pulse width modulation
R	Resistor input
VBB _o	Supply outputs
VBB _s	Supply sensors/module
VBB _R	Supply via relay

7.4 St side / Characteristics of the outputs

CR0133	St side / Characteristics of the outputs												
Q00...03 Q08...11 Digital/ PWM outputs	<table> <tr> <td>Protective circuit for inductive loads</td><td>integrated</td></tr> <tr> <td>Diagnosis wire break</td><td>via current feedback</td></tr> <tr> <td>Diagnosis short circuit</td><td>via current feedback</td></tr> </table>	Protective circuit for inductive loads	integrated	Diagnosis wire break	via current feedback	Diagnosis short circuit	via current feedback						
Protective circuit for inductive loads	integrated												
Diagnosis wire break	via current feedback												
Diagnosis short circuit	via current feedback												
Digital output (B_{H1} and B_{H2})	<table> <tr> <td>Switching voltage</td><td>8...32 V DC</td></tr> <tr> <td>Switching current</td><td>0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)</td></tr> </table>	Switching voltage	8...32 V DC	Switching current	0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)								
Switching voltage	8...32 V DC												
Switching current	0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)												
PWM output (PWM)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Pulse/pause ratio</td><td>1...1000 ‰ (adjustable via software)</td></tr> <tr> <td>Resolution</td><td>1 ‰</td></tr> <tr> <td>Switching current</td><td>0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Pulse/pause ratio	1...1000 ‰ (adjustable via software)	Resolution	1 ‰	Switching current	0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)				
Output frequency	20...250 Hz (per channel)												
Pulse/pause ratio	1...1000 ‰ (adjustable via software)												
Resolution	1 ‰												
Switching current	0.02...2 A / 0.02...4 A (of which 4 with H-bridge function)												
Current-controlled output (PWM _I)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Control range</td><td>0.02...2 A / 0.04...4 A</td></tr> <tr> <td>Setting resolution</td><td>1 mA</td></tr> <tr> <td>Control resolution</td><td>1 mA / 2 mA</td></tr> <tr> <td>Load resistance</td><td>$\geq 6 \Omega$ / $\geq 3 \Omega$ (at 12 V DC) $\geq 12 \Omega$ / $\geq 6 \Omega$ (at 24 V DC)</td></tr> <tr> <td>Accuracy</td><td>± 1.5 % FS</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Control range	0.02...2 A / 0.04...4 A	Setting resolution	1 mA	Control resolution	1 mA / 2 mA	Load resistance	$\geq 6 \Omega$ / $\geq 3 \Omega$ (at 12 V DC) $\geq 12 \Omega$ / $\geq 6 \Omega$ (at 24 V DC)	Accuracy	± 1.5 % FS
Output frequency	20...250 Hz (per channel)												
Control range	0.02...2 A / 0.04...4 A												
Setting resolution	1 mA												
Control resolution	1 mA / 2 mA												
Load resistance	$\geq 6 \Omega$ / $\geq 3 \Omega$ (at 12 V DC) $\geq 12 \Omega$ / $\geq 6 \Omega$ (at 24 V DC)												
Accuracy	± 1.5 % FS												
Q04...07 Q12...15 Digital/ PWM outputs	<table> <tr> <td>Protective circuit for inductive loads</td><td>integrated</td></tr> <tr> <td>Diagnosis wire break</td><td>via current feedback</td></tr> <tr> <td>Diagnosis short circuit</td><td>via current feedback</td></tr> </table>	Protective circuit for inductive loads	integrated	Diagnosis wire break	via current feedback	Diagnosis short circuit	via current feedback						
Protective circuit for inductive loads	integrated												
Diagnosis wire break	via current feedback												
Diagnosis short circuit	via current feedback												
Digital output (B_{H1})	<table> <tr> <td>Switching voltage</td><td>8...32 V DC</td></tr> <tr> <td>Switching current</td><td>0.02...3 A</td></tr> </table>	Switching voltage	8...32 V DC	Switching current	0.02...3 A								
Switching voltage	8...32 V DC												
Switching current	0.02...3 A												
PWM output (PWM)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Pulse/pause ratio</td><td>1...1000 ‰ (adjustable via software)</td></tr> <tr> <td>Resolution</td><td>1 ‰</td></tr> <tr> <td>Switching current</td><td>0.02...3 A</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Pulse/pause ratio	1...1000 ‰ (adjustable via software)	Resolution	1 ‰	Switching current	0.02...3 A				
Output frequency	20...250 Hz (per channel)												
Pulse/pause ratio	1...1000 ‰ (adjustable via software)												
Resolution	1 ‰												
Switching current	0.02...3 A												
Current-controlled output (PWM _I)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Control range</td><td>0.03...3 A</td></tr> <tr> <td>Setting resolution</td><td>1 mA</td></tr> <tr> <td>Control resolution</td><td>2 mA</td></tr> <tr> <td>Load resistance</td><td>$\geq 4 \Omega$ / (at 12 V DC) $\geq 8 \Omega$ / (at 24 V DC)</td></tr> <tr> <td>Accuracy</td><td>± 1.5 % FS</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Control range	0.03...3 A	Setting resolution	1 mA	Control resolution	2 mA	Load resistance	$\geq 4 \Omega$ / (at 12 V DC) $\geq 8 \Omega$ / (at 24 V DC)	Accuracy	± 1.5 % FS
Output frequency	20...250 Hz (per channel)												
Control range	0.03...3 A												
Setting resolution	1 mA												
Control resolution	2 mA												
Load resistance	$\geq 4 \Omega$ / (at 12 V DC) $\geq 8 \Omega$ / (at 24 V DC)												
Accuracy	± 1.5 % FS												

UK

CR0133	St side / Characteristics of the outputs								
Reference voltage $V_{REF\ OUT}$ (sensor supply)	for sensors and joysticks 5/10 V, 400 mA, accuracy $\pm 7\%$ short-circuit proof and overload protected (10 V reference only from a supply voltage $U_s \geq 13\text{ V}$)								
Internal relays	NO contacts for the second switch-off way of the outputs. In series to 2 groups of 8 semiconductor outputs. Forced control via the hardware and additional control via the user program. The relays must always be switched without load!								
	<table border="1"> <tr> <td>Switching current</td><td>0.1...15 A</td></tr> <tr> <td>Overload current</td><td>20 A</td></tr> <tr> <td>Number of operating cycles (without load)</td><td>$\geq 10^6$</td></tr> <tr> <td>Switching time constant</td><td>$\leq 3\text{ ms}$</td></tr> </table>	Switching current	0.1...15 A	Overload current	20 A	Number of operating cycles (without load)	$\geq 10^6$	Switching time constant	$\leq 3\text{ ms}$
Switching current	0.1...15 A								
Overload current	20 A								
Number of operating cycles (without load)	$\geq 10^6$								
Switching time constant	$\leq 3\text{ ms}$								
Load current per output group (VBB_R, VBB_O)	$\leq 12\text{ A}$ (for continuous operation $\leq 6\text{ A}$; i.e. operation $\geq 10\text{ min}$)								
Overload protection (valid for all outputs)	max. 5 minutes (at 100% overload)								
Short-circuit strength to GND	Switch-off of the outputs is carried out via the output driver								

7.5 Ex side / Characteristics of the inputs

CR0133

IN00...03 Analogue / digital inputs

Current input 0...20 mA (A)

Voltage input 0...10 V (A)

Voltage input 0...32 V (A)

Voltage input ratiometric (A)

Digital input (B_{LH})

IN04...05 Digital / resistor inputs

Digital input (B_L)

Ex side / Characteristics of the inputs

Resolution	12 bits
Accuracy	± 1 % FS (in the measuring range 0...20 mA: ± 2 % FS)
Measuring ranges	0...10 V, 0...32 V, 0...20 mA, ratiometric

Input resistance	390 Ω
Input frequency	≤ 1 kHz (default 35 Hz)

Input resistance	65.6 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)

Input resistance	50.7 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)

Input resistance	50.7 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)

Input resistance	3.2 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	> 0.7 U _B
Switch-off level	< 0.3 U _B
Diagnostics* Short circuit to VBB	> 0.95 U _B
Diagnostics* Short circuit to GND / wire break	< 1 V

*) only binary low-side (B_L)

Resolution	12 bits
------------	---------

Input resistance	3.2 kΩ
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	> 0.7 U _B
Switch-off level	< 0.3 U _B
Diagnostics Short circuit to VBB	> 0.95 U _B
Diagnostics Short circuit to GND / wire break	< 1 V
Voltage on the pin when not connected	≤ 0.2 V

UK

CR0133

Resistor input (R)

Ex side / Characteristics of the inputs

Measuring current	< 2.0 mA
Input frequency	50 Hz
Measuring range	16 Ω ...30 k Ω
Accuracy	$\pm 2\%$ FS: 16 Ω ...3 k Ω $\pm 5\%$ FS: 3...15 k Ω $\pm 10\%$ FS: 15...30 k Ω
Diagnostics Short circuit to VBB	> 31 k Ω

**IN06...11
Digital inputs**Digital input (B_{LH})

Resolution	12 bits
Input resistance	3.2 k Ω
Input frequency	≤ 1 kHz (default 35 Hz)
Switch-on level	> 0.7 U _B
Switch-off level	< 0.3 U _B
Diagnostics* Short circuit to VBB	> 0.95 U _B
Diagnostics* Short circuit to GND / wire break	< 1 V

*) only binary low-side (B_L)**IN12...15
Digital / frequency inputs**Digital input (B_{LH})

Resolution	12 bits
Input resistance	3.2 k Ω
Input frequency	≤ 30 kHz
Switch-on level	> 0.35...0.48 U _B
Switch-off level	< 0.29 U _B
Diagnostics* Short circuit to VBB	none
Diagnostics* Short circuit to GND / wire break	none

*) only binary low-side (B_L)

Frequency input (FRQ)

Input resistance	3.2 k Ω
Input frequency	≤ 30 kHz
Switch-on level	> 0.35...0.48 U _B
Switch-off level	< 0.29 U _B

7.6 Ex side / Characteristics of the outputs

CR0133	Ex side / Characteristics of the outputs	
OUT00...01 Digital/ PWM outputs	Protective circuit for inductive loads	integrated
	Diagnosis wire break	via voltage feedback
	Diagnosis short circuit	via voltage feedback
	Diagnosis excessive current	integrated
Digital output (B_H)	Switching voltage	8...32 V DC
	Switching current	0.02...2 A
PWM output (PWM)	Output frequency	20...250 Hz (per channel)
	Pulse/pause ratio	1...1000 ‰ (adjustable via software)
	Resolution	1 ‰
	Switching current	0.02...2 A
Current-controlled output (PWM _I)	Output frequency	20...250 Hz (per channel)
	Control range	0.02...2 A
	Setting resolution	1 mA
	Control resolution	2 mA
	Load resistance	≥ 6 Ω (at 12 V DC) ≥ 12 Ω (at 24 V DC)
	Accuracy	± 1.5 % FS
OUT02...07 Digital/ PWM outputs	Protective circuit for inductive loads	integrated
	Diagnosis wire break	only if switched off $U_{OUT} > 27.5 \% V_{BB_S}$
	Diagnosis short circuit	only in the logic ON state $U_{OUT} < 93.5 \% V_{BB_S}$
Digital output (B_H)	Switching voltage	8...32 V DC
	Switching current	0.02...2 A
PWM output (PWM)	Output frequency	20...250 Hz (per channel)
	Pulse/pause ratio	1...1000 ‰ (adjustable via software)
	Resolution	1 ‰
	Switching current	0.02...2 A
OUT08...09 Digital/ PWM outputs	Protective circuit for inductive loads	integrated
	Diagnosis wire break	none
	Diagnosis short circuit	none
Digital output (B_H)	Switching voltage	8...32 V DC
	Switching current	0.02...2 A

UK

CR0133	Ex side / Characteristics of the outputs										
PWM output (PWM)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Pulse/pause ratio</td><td>1...1000 ‰ (adjustable via software)</td></tr> <tr> <td>Resolution</td><td>1 ‰</td></tr> <tr> <td>Switching current</td><td>0.02...2 A</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Pulse/pause ratio	1...1000 ‰ (adjustable via software)	Resolution	1 ‰	Switching current	0.02...2 A		
Output frequency	20...250 Hz (per channel)										
Pulse/pause ratio	1...1000 ‰ (adjustable via software)										
Resolution	1 ‰										
Switching current	0.02...2 A										
OUT08_A...09_A Analogue outputs	<table> <tr> <td>Voltage range</td><td>8...32 V</td></tr> <tr> <td>Current rating</td><td>< 5 mA</td></tr> <tr> <td>Output voltage</td><td>0.2...10 V</td></tr> <tr> <td>Accuracy</td><td>± 6 % FS</td></tr> <tr> <td>Residual ripple at 120 Hz</td><td>80 mV</td></tr> </table>	Voltage range	8...32 V	Current rating	< 5 mA	Output voltage	0.2...10 V	Accuracy	± 6 % FS	Residual ripple at 120 Hz	80 mV
Voltage range	8...32 V										
Current rating	< 5 mA										
Output voltage	0.2...10 V										
Accuracy	± 6 % FS										
Residual ripple at 120 Hz	80 mV										
OUT10...11 Digital/ PWM outputs	<table> <tr> <td>Protective circuit for inductive loads</td><td>integrated</td></tr> <tr> <td>Diagnosis wire break</td><td>none</td></tr> <tr> <td>Diagnosis short circuit</td><td>none</td></tr> </table>	Protective circuit for inductive loads	integrated	Diagnosis wire break	none	Diagnosis short circuit	none				
Protective circuit for inductive loads	integrated										
Diagnosis wire break	none										
Diagnosis short circuit	none										
Digital output (B _H)	<table> <tr> <td>Switching voltage</td><td>8...32 V DC</td></tr> <tr> <td>Switching current</td><td>0.02...4 A</td></tr> </table>	Switching voltage	8...32 V DC	Switching current	0.02...4 A						
Switching voltage	8...32 V DC										
Switching current	0.02...4 A										
PWM output (PWM)	<table> <tr> <td>Output frequency</td><td>20...250 Hz (per channel)</td></tr> <tr> <td>Pulse/pause ratio</td><td>1...1000 ‰ (adjustable via software)</td></tr> <tr> <td>Resolution</td><td>1 ‰</td></tr> <tr> <td>Switching current</td><td>0.02...4 A</td></tr> </table>	Output frequency	20...250 Hz (per channel)	Pulse/pause ratio	1...1000 ‰ (adjustable via software)	Resolution	1 ‰	Switching current	0.02...4 A		
Output frequency	20...250 Hz (per channel)										
Pulse/pause ratio	1...1000 ‰ (adjustable via software)										
Resolution	1 ‰										
Switching current	0.02...4 A										
OUT12...15 Digital outputs	<table> <tr> <td>Protective circuit for inductive loads</td><td>integrated</td></tr> <tr> <td>Diagnosis wire break</td><td>none</td></tr> <tr> <td>Diagnosis short circuit</td><td>none</td></tr> </table>	Protective circuit for inductive loads	integrated	Diagnosis wire break	none	Diagnosis short circuit	none				
Protective circuit for inductive loads	integrated										
Diagnosis wire break	none										
Diagnosis short circuit	none										
Digital output (B _H)	<table> <tr> <td>Switching voltage</td><td>8...32 V DC</td></tr> <tr> <td>Switching current</td><td>0.02...2 A</td></tr> </table>	Switching voltage	8...32 V DC	Switching current	0.02...2 A						
Switching voltage	8...32 V DC										
Switching current	0.02...2 A										
Load current per output group (VBB ₁ , VBB ₂)	≤ 12 A (for continuous operation ≤ 9 A; i.e. operation ≥ 10 min)										
Overload protection (valid for all outputs)	max. 5 minutes (at 100% overload)										
Short-circuit strength to GND	Switch-off of the outputs is carried out via the output driver										


7.7 St side / Wiring

CR0133

Technical data

Wiring

St side



Abbreviations

A	analogue
B _H	binary high side
B _L	binary low side
FRQ	frequency / pulse inputs with levels depending on the supply voltage
FRQ*	frequency / pulse inputs with fixed levels
H	H-bridge function
PWM	pulse width modulation
PWM _I	pulse width modulation, current-controlled
R	resistor input
VBB _s	supply sensors/module
VBB...	supply output group


7.8 Ex side / Wiring

CR0133

Technical data

Wiring

Ex side



Abbreviations

A	analogue
B _H	binary high side
B _L	binary low side
FRQ	frequency / pulse inputs with levels depending on the supply voltage
FRQ*	frequency / pulse inputs with fixed levels
H	H-bridge function
PWM	pulse width modulation
PWM _I	pulse width modulation, current-controlled
R	resistor input
VBB _s	supply sensors/module
VBB _o	supply output group

St	standard side
Ex	extended side

If not otherwise specified, the data apply to the St and Ex side.

8 Maintenance, repair and disposal

The device is maintenance-free.

- ▶ Do not open the housing as the device does not contain any components which must be maintained by the user. The device must only be repaired by the manufacturer.
- ▶ Dispose of the device in accordance with the national environmental regulations.

9 Approvals / standards

Test standards and regulations (→ 7 Technical data)

The EC Declaration of Conformity and approvals can be found at:
www.ifm.com → Data sheet search → CR0133 → More information

UK