

## **Technical data sheet** Multiple light beam safety device receiver

Part no.: 66055700 MLD320-XR4LM



The Sensor People In der Braike 1, 73277 Owen

Leuze electronic GmbH + Co. KG info@leuze.com • www.leuze.com

Phone: +49 7021 573-0 • Fax: +49 7021 573-199

We reserve the right to make technical changes eng • 2020-06-17

### **Technical data**

## Leuze

Series	MLD 300
Device type	Receiver
Special design	
	Integrated status indicator
Special design	Integrated status indicator Reflective element for laser alignment aid
Functions	
Functions	Contactor monitoring (EDM), selectable
	Start/restart interlock (RES), selectable
Characteristic parameters	
Туре	2, IEC/EN 61496
SIL	1, IEC 61508
SILCL	1, IEC/EN 62061
Performance Level (PL)	c, EN ISO 13849-1
MTTF <sub>d</sub>	204 years, EN ISO 13849-1
PFH	1.2E-08 per hour
Mission time T <sub>M</sub>	20 years, EN ISO 13849-1
Category	3, EN ISO 13849
Optical data	
Number of beams	4 Piece(s)
Beam spacing	300 mm
Electrical data	
Protective circuit	Overvoltage protection
	Short circuit protected
Performance data	
Supply voltage U <sub>B</sub>	24 V, DC, -20 20 %
Current consumption, max.	150 mA, Without external load
Fuse	External with max. 3 A
Inputo	
Inputs Number of digital switching inputs	3 Piece(s)
Switching inputs	
Туре	Digital switching input
Switching voltage high, min.	18.2 V
Switching voltage low, max.	2.5 V
Switching voltage, typ.	23 V
Voltage type	DC
Switching current, max.	5 mA
Digital switching input 1	
Digital switching input 1 Assignment	Connection 1, pin 1
	Connection 1, pin 1 Control input for start/restart interlock
Assignment	Connection 1, pin 1 Control input for start/restart interlock (RES)
Assignment Function	Control input for start/restart interlock
Assignment	Control input for start/restart interlock (RES)
Assignment Function Digital switching input 2	Control input for start/restart interlock
Assignment Function Digital switching input 2 Assignment Function	Control input for start/restart interlock (RES) Connection 1, pin 3 Control input for contactor monitoring
Assignment Function Digital switching input 2 Assignment Function Digital switching input 3	Control input for start/restart interlock (RES) Connection 1, pin 3 Control input for contactor monitoring (EDM)
Assignment Function Digital switching input 2 Assignment Function	Control input for start/restart interlock (RES) Connection 1, pin 3 Control input for contactor monitoring

#### Outputs

Outputs	
Number of safety-related switching outputs (OSSDs)	2 Piece(s)
Number of digital switching outputs	1 Piece(s)
Safety-related switching outp	uts
Туре	Safety-related switching output OSSD
Switching voltage high, min.	18.2 V
Switching voltage low, max.	2.5 V
Switching voltage, typ.	23 V
Voltage type	DC
Current load, max.	380 mA
Load inductivity	2,200,000 µH
Load capacity	0.3 µF
Residual current, max.	0.2 mA
Residual current, typ.	0.002 mA
Voltage drop	1 V
Safety-related switching ou	
Assignment	Connection 1, pin 6
Switching element	Transistor, PNP
Safety-related switching ou	itput 2
Assignment	Connection 1, pin 5
Switching element	Transistor, PNP
Switching outputs	
Туре	Digital switching output
Switching voltage high, min.	18.2 V
Switching voltage low, max.	2.5 V
Switching voltage, typ.	23 V
Voltage type	DC
Switching output 1	
Assignment	Connection 1, pin 1
Switching element	Transistor, PNP
iming	
lesponse time	25 ms
lestart delay time	100 ms
Connection	
lumber of connections	1 Piece(s)
Connection 1	
Function	Machine interface
Type of connection	Connector
Thread size	M12
Material	Metal
No. of pins	8 -pin
Cable properties	
Permissible conductor cross section, typ.	0.25 mm²
Length of connection cable, max.	100 m
Permissible cable resistance to	200 Ω
load, max.	

The Sensor People In der Braike 1, 73277 Owen

Leuze electronic GmbH + Co. KG info@leuze.com • www.leuze.com Phone: +49 7021 573-0 • Fax: +49 7021 573-199

### **Technical data**

# Leuze

#### Mechanical data

Dimension (W x H x L)	52 mm x 1,000 mm x 64.7 mm
Housing material	Metal, Aluminum
Lens cover material	Plastic / PMMA
Material of end caps	Diecast zinc
Net weight	2,200 g
Housing color	Yellow, RAL 1021
Type of fastening	Groove mounting
	Swivel mount

#### **Operation and display**

Type of display	LED
Number of LEDs	2 Piece(s)

#### **Environmental data**

Ambient temperature, operation	-30 55 °C
Ambient temperature, storage	-40 75 °C
Relative humidity (non-condensing)	0 95 %

## **Dimensioned drawings**

All dimensions in millimeters

Certifications	
Degree of protection	IP 67
Protection class	III
Certifications	c CSA US
	c TÜV NRTL US
	TÜV Süd
US patents	US 6,418,546 B
	US 7,741,595 B
Classification	
Customs tariff number	85365019
eCl@ss 8.0	27272703
eCl@ss 9.0	27272703
ETIM 5.0	EC001832
ETIM 6.0	EC001832



	4		1000		
	48,5	300	. 300	300	51,5
-					
52				υ	

#### **Electrical connection**

**Connection 1** 

Function	Machine interface
Type of connection	Connector
Thread size	M12
Туре	Male
Material	Metal
No. of pins	8 -pin
Encoding	A-coded

#### **Electrical connection**

## Leuze

Pin	Pin assignment	Conductor color
1	RES/OSSD status signal	White
2	+24V	Brown
3	EDM	Green
4	MODE	Yellow
5	OSSD2	Gray
6	OSSD1	Pink
7	0 V	Blue
8	n.c.	Red



LED	Display	Meaning
1	Red, continuous light	OSSD off.
	Green, continuous light	OSSD on
	Red, flashing, 1 Hz	External error
	Red, flashing, 10 Hz	Internal error
	Green, flashing, 1 Hz	Weak signal, device not optimally aligned or soiled.
2	Yellow, continuous light	Start/restart interlock locked.

#### Suitable transmitters

 Part no.	Designation	Article	Description
66002700	MLD300-XT4L	Multiple light beam safety device transmitter	Operating range: 20 70 m Number of beams: 4 Piece(s) Beam spacing: 300 mm Connection: Connector, M12, Metal, 5 -pin Special design: Integrated laser alignment aid

#### Part number code

Part designation: MLDxyy-zab/t	
MLD	Multiple light beam safety device
x	Series 3: MLD 300 5: MLD 500
уу	Function classes 00: transmitter 10: automatic restart 12: external testing 20: EDM/RES 30: muting 35: timing controlled 4-sensor muting
z	Device type T: transmitter R: receiver RT: transceiver xT: transmitter with high range xR: receiver for high range
а	Number of beams

### Part number code

MLD	Multiple light beam safety device
b	Option L: integrated laser alignment aid (for transmitter/receiver) M: integrated status indicator (MLD 320, MLD 520) or integrated status and muting indicator (MLD 330, MLD 335, MLD 510/A, MLD 530, MLD 535) E: connection socket for external muting indicator (AS-i models only)
/t	Safety-related switching outputs (OSSDs), connection technology -: transistor output, M12 plug A: integrated AS-i interface, M12 plug, (safety bus system)
	Note
6	S A list with all available device types can be found on the Leuze website at www.leuze.com.

#### Accessories

#### Services

	Part no.	Designation	Article	Description
()	S981050	CS40-I-140	Safety inspection "Safety light barriers"	Details: Checking of a safety light barrier application in accordance with current standards and guidelines. Inclusion of the device and machine data in a database, production of a test log per application. Conditions: It must be possible to stop the machine, support provided by customer's employees and access to the machine for Leuze employees must be ensured. Restrictions: Travel costs and accommodation expenses charged separately and according to expenditure.
	S981046	CS40-S-140	Start-up support	Details: For safety devices including stopping time measurement and initial inspection. Conditions: Devices and connection cables are already mounted, price not including travel costs and, if applicable, accommodation expenses. Restrictions: Max. 2 h., no mechanical (mounting) and electrical (wiring) work performed, no changes (attachments, wiring, programming) to third-party components in the nearby environment.

	Note
6	♣ A list with all available accessories can be found on the Leuze website in the Download tab of the article detailed page.