

Technical data sheet Multiple light beam safety device receiver Part no.: 66056100

MLD320-R2L



The Sensor People In der Braike 1, 73277 Owen

Leuze electronic GmbH + Co. KG info@leuze.com • www.leuze.com

Phone: +49 7021 573-0 • Fax: +49 7021 573-199

We reserve the right to make technical changes eng • 2020-06-17

. . . .

Leuze

| Basic data | |
|--|--|
| Series | MLD 300 |
| Device type | Receiver |
| Special design | |
| Special design | Reflective element for laser alignment aid |
| Functions | aiu |
| | |
| Functions | Contactor monitoring (EDM), selectable Start/restart interlock (RES), selectable |
| Characteristic parameters | |
| Туре | 2, IEC/EN 61496 |
| SIL | 1, IEC 61508 |
| SILCL | 1, IEC/EN 62061 |
| Performance Level (PL) | c, EN ISO 13849-1 |
| MTTF _d | 204 years, EN ISO 13849-1 |
| PFH _D | 1.2E-08 per hour |
| Mission time T _M | 20 years, EN ISO 13849-1 |
| Category | 3, EN ISO 13849 |
| Optical data | |
| Number of beams | 2 Piece(s) |
| Beam spacing | 500 mm |
| Electrical data | |
| Protective circuit | Overvoltage protection |
| | Short circuit protected |
| | |
| Performance data | |
| Supply voltage U _B | 24 V, DC, -20 20 % |
| Current consumption, max. | 150 mA, Without external load |
| Fuse | |
| | External with max. 3 A |
| Innuts | External with max. 3 A |
| Inputs Number of digital switching inputs | |
| Inputs Number of digital switching inputs | 3 Piece(s) |
| Number of digital switching inputs Switching inputs | 3 Piece(s) |
| Number of digital switching inputs Switching inputs Type | 3 Piece(s) Digital switching input |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. | 3 Piece(s) Digital switching input 18.2 V |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. | 3 Piece(s) Digital switching input 18.2 V 2.5 V |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Digital switching input 2 | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 Control input for start/restart interlock (RES) |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Digital switching input 2 Assignment | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 Control input for start/restart interlock (RES) Connection 1, pin 3 |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Digital switching input 2 | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 Control input for start/restart interlock (RES) |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Digital switching input 2 Assignment | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 Control input for start/restart interlock (RES) Connection 1, pin 3 Control input for contactor monitoring |
| Number of digital switching inputs Switching inputs Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Digital switching input 2 Assignment Function | 3 Piece(s) Digital switching input 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 1 Control input for start/restart interlock (RES) Connection 1, pin 3 Control input for contactor monitoring |

| Outputs | | |
|--|--------------------------------------|--|
| Number of safety-related switching outputs (OSSDs) | 2 Piece(s) | |
| Number of digital switching outputs | 1 Piece(s) | |
| Safety-related switching output | uts | |
| Туре | Safety-related switching output OSSD | |
| Switching voltage high, min. | 18.2 V | |
| Switching voltage low, max. | 2.5 V | |
| Switching voltage, typ. | 23 V | |
| Voltage type | DC | |
| Current load, max. | 380 mA | |
| Load inductivity | 2,200,000 µH | |
| Load capacity | 0.3 µF | |
| Residual current, max. | 0.2 mA | |
| Residual current, typ. | 0.002 mA | |
| Voltage drop | 1 V | |
| Safety-related switching ou | tout 1 | |
| Assignment | Connection 1, pin 6 | |
| Switching element | Transistor, PNP | |
| | | |
| Safety-related switching ou | tput 2 | |
| Assignment | Connection 1, pin 5 | |
| Switching element | Transistor, PNP | |
| Switching outputs | | |
| Туре | Digital switching output | |
| Switching voltage high, min. | 18.2 V | |
| Switching voltage low, max. | 2.5 V | |
| Switching voltage, typ. | 23 V | |
| Voltage type | DC | |
| | | |
| Switching output 1 | Connection 4 min 4 | |
| Assignment | Connection 1, pin 1 | |
| Switching element | Transistor, PNP | |
| Fiming | | |
| Response time | 25 ms | |
| Restart delay time | 100 ms | |
| Connection | | |
| Number of connections | 1 Piece(s) | |
| Connection 1 | | |
| Function | Machine interface | |
| Type of connection | Connector | |
| Thread size | M12 | |
| Material | Metal | |
| No. of pins | 8 -pin | |
| Cable properties | | |
| Permissible conductor cross section, typ. | 0.25 mm ² | |
| Length of connection cable, max. | 100 m | |
| Permissible cable resistance to | 200 Ω | |
| load, max. | | |
| | | |

 Leuze electronic GmbH + Co. KG
 info@leuze.com • www.leuze.com
 We reserve the rig

 The Sensor People
 In der Braike 1, 73277 Owen
 Phone: +49 7021 573-0 • Fax: +49 7021 573-199
 we reserve the rig

Technical data

Leuze

Mechanical data

| Dimension (W x H x L) | 52 mm x 600 mm x 64.7 mm |
|-----------------------|--------------------------|
| Housing material | Metal, Aluminum |
| Lens cover material | Plastic / PMMA |
| Material of end caps | Diecast zinc |
| Net weight | 1,400 g |
| Housing color | Yellow, RAL 1021 |
| Type of fastening | Groove mounting |
| | Swivel mount |
| | |

Operation and display

| Type of display | LED |
|-----------------|------------|
| Number of LEDs | 2 Piece(s) |
| | |

Environmental data

| Ambient temperature, operation | -30 55 °C |
|------------------------------------|-----------|
| Ambient temperature, storage | -40 75 °C |
| Relative humidity (non-condensing) | 0 95 % |

Dimensioned drawings

All dimensions in millimeters

| Certifications | | | | |
|-----------------------|----------------|--|--|--|
| Degree of protection | IP 67 | | | |
| Protection class | III | | | |
| Certifications | c CSA US | | | |
| | c TÜV NRTL US | | | |
| | TÜV Süd | | | |
| US patents | US 6,418,546 B | | | |
| | US 7,741,595 B | | | |
| Classification | | | | |
| Customs tariff number | 85365019 | | | |
| eCl@ss 8.0 | 27272703 | | | |
| eCl@ss 9.0 | 27272703 | | | |
| ETIM 5.0 | EC001832 | | | |
| ETIM 6.0 | EC001832 | | | |

Electrical connection


Connection 1

| Function | Machine interface |
|--------------------|-------------------|
| Type of connection | Connector |
| Thread size | M12 |
| Туре | Male |
| Material | Metal |
| No. of pins | 8 -pin |
| Encoding | A-coded |

Pin Pin assignment

Conductor color

| 1 | RES/OSSD status signal | White |
|---|------------------------|--------|
| 2 | +24V | Brown |
| 3 | EDM | Green |
| 4 | MODE | Yellow |
| 5 | OSSD2 | Gray |
| 6 | OSSD1 | Pink |
| 7 | 0 V | Blue |
| 8 | n.c. | Red |
| | | |



Operation and display

Leuze

| LED | Display | Meaning |
|-----|--------------------------|--|
| 1 | Red, continuous light | OSSD off. |
| | Green, continuous light | OSSD on |
| | Red, flashing, 1 Hz | External error |
| | Red, flashing, 10 Hz | Internal error |
| | Green, flashing, 1 Hz | Weak signal, device not optimally aligned or soiled. |
| 2 | Yellow, continuous light | Start/restart interlock locked. |

Suitable transmitters

| Part no. | Designation | Article | Description |
|--------------|-------------|---|---|
| 66002100 | MLD300-T2L | Multiple light beam safety device transmitter | Operating range: 0.5 50 m Number of beams: 2 Piece(s) Beam spacing: 500 mm Connection: Connector, M12, Metal, 5 -pin Special design: Integrated laser alignment aid |

Part number code

| MLD | Multiple light beam safety device |
|-----|---|
| x | Series 3: MLD 300 5: MLD 500 |
| уу | Function classes 00: transmitter 10: automatic restart 12: external testing 20: EDM/RES 30: muting 35: timing controlled 4-sensor muting |
| Z | Device type T: transmitter R: receiver RT: transceiver xT: transmitter with high range xR: receiver for high range |
| а | Number of beams |
| b | Option L: integrated laser alignment aid (for transmitter/receiver) M: integrated status indicator (MLD 320, MLD 520) or integrated status and muting indicator (MLD 330, MLD 335, MLD 510/A, MLD 530, MLD 535) E: connection socket for external muting indicator (AS-i models only) |
| /t | Safety-related switching outputs (OSSDs), connection technology -: transistor output, M12 plug A: integrated AS-i interface, M12 plug, (safety bus system) |
| Ν | lote |
| 6 | A list with all available device types can be found on the Leuze website at www.leuze.com. |

Accessories

Leuze

Services

| | Part no. | Designation | Article | Description |
|------------|----------|-------------|--|---|
| \bigcirc | S981050 | CS40-I-140 | Safety inspection "Safety light barriers" | Details: Checking of a safety light barrier application in accordance with current standards and guidelines. Inclusion of the device and machine data in a database, production of a test log per application. Conditions: It must be possible to stop the machine, support provided by customer's employees and access to the machine for Leuze employees must be ensured. Restrictions: Travel costs and accommodation expenses charged separately and according to expenditure. |
| | S981046 | CS40-S-140 | Start-up support | Details: For safety devices including stopping time measurement and initial inspection. Conditions: Devices and connection cables are already mounted, price not including travel costs and, if applicable, accommodation expenses. Restrictions: Max. 2 h., no mechanical (mounting) and electrical (wiring) work performed, no changes (attachments, wiring, programming) to third-party components in the nearby environment. |

| | Note |
|---|--|
| 0 | Sector A list with all available accessories can be found on the Leuze website in the Download tab of the article detailed page. |