латчи

Small size photoelectric sensors **PSS** series



Features

- Universal housing, an ideal replacement for a wide range of sensor types;
- IP67, suitable for harsh environments;
- Fast and stable setting;
- NO and NC are switchable;
- Visible light spots for easy installation and commissioning.



Model

NPN NO/NC	PSS-BC40DNB-E2	PNP NO/NC	PSS-BC40DPB-E2
Specifications			
Detection type	Diffuse reflection	Hysteresis	320%
Rated distance	40cm	Indicator	Green LED: power, stable
Light source	Infrared (940nm)		Yellow LED: output, short circuit or overload
Output	NPN NO/NC or PNP NO/NC	Anti-ambient light	Anti-sunlight interference ≤ 10,000lux;
Response time	≤0.5ms		Incandescent light interference ≤ 3,000lux
Supply voltage	1030 VDC	Operating temperature	-2555 °C
Consumption current	≤20mA	Storage temperature	-3570 °C
Load current	≤200mA	Protection degree	IP67
Voltage drop	≤1V	Certification	CE
Distance adjustment	Single-turn potentiometer	Material	Housing: PC+ABS; Filter: PMMA
Circuit protection	Short-circuit, overload, reverse polarity protection	Annex	M18 nut (2PCS), instruction manual
Connection	M12 4-core connector		
NO/NC adjustment	Feet 2 is connected to the positive pole or hang up, NO mode; Feet 2 is connected to the negative pole, NC mode		

Remarks: ①Detection object is 90% white card with size 20cm * 20cm;

(2) The green LED becomes weaker, which means that the signal is weaker and the sensor is unstable; The yellow LED flashes, which means that the sensor is shorted or overloaded;

Dimensions **Circuit Diagrams** NPN Floating <u>) BN</u> Output indication (Yellow) Load 30V 0 BK Output 0 4 : OUT 2 : -NC/+NO Photoelectrie sensor main circuit 9 3<u>BN</u> \odot 2)WH NO/NC 2 Stability indication (Green) 46.2 PNP Operation LED Floating 2.1 1 BN yellow Receive Output indication (Yellow) × Sol M18×1 BK ø16.7 Output 0 \bigcirc Photoelectric sensor main circuit Load Emitter S <u>э в</u>и Power LED green \bigcirc 9 WH NO/NC Stability indication (Green)

«