



SRB201LC

- 1 Signalling output
- 2 safety contacts, STOP 0
- Suitable for signal processing of potential-free outputs, e.g. emergency stop command devices, position switches and solenoid interlocks

Data

Ordering data

	SRB201LC
	101212555
EAN (European Article Number)	4030661448916
eCl@ss number, Version 9.0	27-37-18-19
Available until	31.12.2022

Approval - Standards

TÜV
EAC

General data

	SRB201LC
	IEC 61508
	IEC/EN 60204-1
	ISO 13849-1
	EN 60947-5-1
	EN 60068-2-78
Enclosure material	Glass-fibre reinforced thermoplastic, ventilated
Material of the contacts, electrical	AgSn0. self-cleaning, positive drive
Gross weight	200 g

General data - Features

Stop-Category	1
---------------	---

Wire breakage detection	Yes
Feedback circuit	Yes
Automatic reset function	Yes
Earth connection detection	Yes
Integral System Diagnostics, status	Yes
Number of LEDs	3
Number of openers	2
Number of undelayed semi-conductor outputs with signaling function	1
Number of safety contacts	2
Number of signalling outputs	1

Safety appraisal

EN 60947-5-1
IEC 61508

Safety appraisal - Relay outputs

Performance level, stop 0, up to	e
Category, Stop 0	4
Diagnostic Coverage (DC) Level, Stop 0	$\geq 99 \%$
PFH-Value Stop 0	$2.00 \times 10^{-8} /h$
Safety Integrity Level (SIL), Stop 0, applicable for	3
Mission time	20 Year(s)
Common Cause Failure (CCF), minimum	65

Mechanical data

Mounting	Snaps onto standard DIN rail to EN 60715
Mechanical life, minimum	10,000,000 Operations

Mechanical data - Connection technique

Terminal Connector	Screw connection rigid or flexible
Terminal designations	IEC/EN 60947-1 0.25 mm ² 2.5 mm ²
Tightening torque of Clips	0.6 Nm

Mechanical data - Dimensions

Width	22.5 mm
Height	100 mm
Depth	121 mm

Ambient conditions

	IP40
	IP54
	IP20
Ambient temperature, minimum	-25 °C
Ambient temperature, maximum	+60 °C
Storage and transport temperature, minimum	-40 °C
Storage and transport temperature, maximum	+85 °C
Resistance to vibrations to EN 60068-2-6	10...55 Hz, Amplitude 0.35 mm, $\pm 15\%$
	10 g / 11 ms

Ambient conditions - Insulation value

Rated impulse withstand voltage	4 kV
	III
	2

Electrical data

Frequency range	60 Hz
	24 VAC -15% / +10%
Rated AC voltage for controls, 50 Hz, minimum	20.4 VAC
Rated control voltage at AC 50 Hz, maximum	26.4 VAC
Rated AC voltage for controls, 60 Hz, minimum	20.4 VAC
Rated control voltage at AC 60 Hz, maximum	26.4 VAC
Rated AC voltage for controls at DC minimum	20.4 VDC
Rated control voltage at DC, maximum	28.8 VDC
Electrical power consumption	2 W
Electrical power consumption	5.2 VA
Contact resistance, maximum	0.1 Ω

Note (Contact resistance)	in new state
Drop-out delay in case of power failure, typically	80 ms
Drop-out delay in case of emergency, typically	20 ms
Pull-in delay at automatic start, maximum, typically	100 ms
Pull-in delay at RESET, typically	20 ms

Electrical data - Safe relay outputs

Voltage, Utilisation category AC15	230 VAC
Current, Utilisation category AC-15	6 A
Voltage, Utilisation category DC13	24 VDC
Current, Utilisation category DC13	6 A
Switching capacity, minimum	10 VDC
Switching capacity, minimum	10 mA
Switching capacity, maximum	250 VAC
Switching capacity, maximum	8 A

Electrical data - Digital inputs

Conduction resistance, maximum 40 Ω

Electrical data - Relay outputs (auxiliary contacts)

Switching capacity, maximum	24 VDC
Switching capacity, maximum	2 A

Electrical data - Electromagnetic compatibility (EMC)

EMC rating	EMC-Directive
------------	---------------

Status indication

Indicated operating states	Position relay K2
	Position relay K1
	Internal operating voltage U _i

Other data

Note (applications)	Guard system
	Emergency-Stop button
	Pull-wire emergency stop switches
	Safety light curtain

Notes

Note (General) Inductive loads (e.g. contactors, relays, etc.) are to be suppressed by means of a suitable circuit.

Circuit example

Note (Wiring diagram)

The wiring diagram is shown with guard doors closed and in de-energised condition.

Relay outputs: Suitable for 2 channel control, for increase in capacity or number of contacts by means of contactors or relays with positive-guided contacts.

Automatic start: The automatic start is programmed by connecting the feedback circuit to the terminals X1/X2. If the feedback circuit is not required, establish a bridge.

The control recognises cross-short, cable break and earth leakages in the monitoring circuit.

Input level: The example shows a 2-channel control of a guard door monitoring with two position switches, whereof one with positive break, external reset button (R); cross-wire monitoring and feedback circuit (H2)

In case of a 1-channel control, connect the NC contact to the operating voltage and bridge S11/S12 and S21/S22.

Pictures

Photo/Product/Catalogue



ID: ksrb2f30

| 83,8 kB | .png | 74.083 x 147.461 mm - 210 x 418

Pixel - 72 dpi

| 700,6 kB | .jpg | 265.289 x 529.167 mm - 752 x 1500

Pixel - 72 dpi

Graphic/Product/Wiring




ID: ksrb2i54

| 615,7 kB | .jpg | 352.778 x 1571.272 mm - 1000 x

4454 Pixel - 72 dpi


Graphic/Product/Wiring



ID: ksrb2I55

| 106,2 kB | .jpg | 352.778 x 273.756 mm - 1000 x 776
Pixel - 72 dpi

Graphic/Product/Wiring



ID: ksrb2I56

| 70,5 kB | .jpg | 352.425 x 442.736 mm - 999 x 1255
Pixel - 72 dpi

Graphic/Product/Icon

K	n-op/y	t-cycle
20 %	525.600	1,0 min
40 %	210.240	2,5 min
60 %	75.087	7,0 min
80 %	30.918	17,0 min
100 %	12.223	43,0 min

ID: kformm02

| 191,1 kB | .jpg | 352.778 x 246.592 mm - 1000 x 699
Pixel - 72 dpi

K.A. Schmersal GmbH & Co. KG, Möddinghofe 3, D-42279 Wuppertal

The details and data referred to have been carefully checked. Images may diverge from original. Further technical data can be found in the manual. Technical amendments and errors possible.

Generated on 422021-01-31T12:26:42+01:001201Europe/BerlinSun, 31 Jan 2021 12:26:42

+010042pmSunday.31pm31Europe/BerlinCET2601Europe/BerlinJanuary2021Sun, 31 Jan 2021 12:26:42

+010001pm31