Slot grid sensor



CE

Model Number

RAL100-IR/32/98

Slot grid sensor with 3-pin, M8 x 1 connector

Features

- · Compact slot grid sensor
- Open frame with wide detection area ٠
- Optimized for the detection of small ٠ parts
- Option to suppress stationary objects ٠
- Detection of very small guided and ٠ non-guided parts in free fall

Product information

Slot grid sensors are ideal for filling and counting objects in feed devices. In contrast to standard photoelectric slot sensors, the slot grid sensors have an entire field for object detection with a maximum response time of 100 μs and a minimum object size of 1 mm. When using dynamic mode, only moving objects are detected.





Electrical connection

Dimensions





Pinout



ance with EN 60947-5-2 (brown) (blue) (black) BN BU BK

Indicators/operating means



1	Functional display	yellow
2	Time/static	
3	Sensitivity adjuster	

Pepperl+Fuchs Group www.pepperl-fuchs.com

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com ⁵ PEPPERL+FUCHS

1

RAL100-IR/32/98

Technical data	Accessories		
General specifications	V3-WM-2M-PUR		
Light source IRED		Female cordset single-ended, M8, 3-pin, PUR cable	
Light type modula	ated infrared light		
Marking CE			
Slot width 100 m	n	Other suitable accessories can be found at	
Slot depth 98 mm		www.pepperl-fuchs.com	
Ambient light limit 10000	Lux		
Resolution 2 mm			
Temperature influence < 10 %	6		
active zone 100 m	m x 94 mm		
Indicators/operating means			
Function indicator LED, y	ellow		
Control elements sensiti	vity adjustment		
Control elements Time a	djuster for Pulse stretching and Dynamic/static operation		
Electrical specifications			
Operating voltage U _B 24 V D	C ± 20 %		
No-load supply current I ₀ < 70 m	A		
Output			
Switching type dark or	n		
	output, short-circuit protected, reverse polarity protected, ollector		
Switching voltage max. 3	0 V DC		
Switching current 200 m/	A		
Voltage drop U _d < 2.5 V	1		
Switching frequency f 5000 H	łz		
Repeat accuracy R 0.1 m	n		
Pulse extension 0.1 7	150 ms		
Conformity			
Product standard EN 609	947-5-2		
Ambient conditions			
Ambient temperature -10	60 °C (14 140 °F)		
Mechanical specifications			
Housing width 20 mm			
Housing height 140 mi	m		
Degree of protection IP67			
.	nnector, 3-pin		
Material			
Housing black a	anodized aluminum		
Optical face glass			
Mass 400 g			

Resolution

Potentiometer setting	RAL-50	RAL-70	RAL-100	RAL-150
Minimal	0.5 mm	0.8 mm	1.0 mm	1.2 mm
Center	4.0 mm	8.0 mm	10.0 mm	15.0 mm
Maximum	8.0 mm	15.0 mm	25.0 mm	50.0 mm

The information on the maximum resolution (smallest detectable object) relates to the center of the slot grid sensor.

Configuration information

The device is set to large parts by turning the sensitivity adjustment potentiometer clockwise and to small parts by turning the sensitivity adjustment potentiometer counterclockwise.

The "time/static" potentiometer can be used both to select pulse extension in dynamic operation and to select static/dynamic operation. Static operation is selected by turning the potentiometer counterclockwise as far as it will go. Pulse extension is set to 1 ms. Pulse extension can be adjusted between 150 ms and 0 ms by turning the potentiometer clockwise.

In static operation, the output remains set while the object is within the frame. The switching threshold is not automatically tracked in this operating mode. Temperature fluctuations and dirt may trigger a switching operation.

In dynamic operation, the output is set only to the specified pulse extension. Objects that extend into the frame are hidden.

If the device becomes dirty in dynamic operation, the output is set statically at 50% reception signal.

190730_eng.xml Release date: 2020-01-15 09:26 Date of issue: 2020-01-15

2

Germany: +49 621 776 1111

fa-info@de.pepperl-fuchs.com