Thru-beam sensor





Model Number

LD31/LV31-6559/25/38/115

Thru-beam sensor with 2 m fixed cable

Features

- Operating voltage DC ٠
- Highly visible LED •
- Protection class II •
- Relay output •
- Compact and stable housing •

Dimensions



Electrical connection



Release date: 2020-01-20 03:05 Date of issue: 2020-01-20 271173_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group

www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

Technical data			Accessories
System components			OMH-RL31-01
Emitter		LD31-6559	
Receiver		LV31-6559/25/38	Mounting bracket
General specifications			OMH-RL31-02
Effective detection range		0 30 m	
Threshold detection range		43 m	Mounting bracket narrow
Light source		LED	OMH-RL31-03
•			Mounting bracket narrow
Light type Alignment aid		modulated visible red light , 630 nm LED yellow: 1. LED illuminates: Sufficient light signal received, emitter and receiver alignment is correct 2. LED flashes: Reaching switching point 3. LED off: Light beam is interrupted or the alignment is out	OMH-RL31-04 Mounting aid for round steel ø 12 m sheet 1.5 mm 3 mm
Diameter of the light spot		approx. 800 mm at a distance of 30 m	OMH-RL31-05
Angle of divergence		Emitter: 0.5 °, Receiver: 1.5 °	Mounting bracket for mounting on fl
Ambient light limit		50000 Lux ; according EN 60947-5-2	surfaces with 2 M4 screws
Functional safety related para	ameters		surfaces with 2 M4 screws
MTTF _d		620 a	OMH-RL31-06
Mission Time (T _M)		20 a	Stainless steel mounting bracket wit
Diagnostic Coverage (DC)		0%	
		- /·	adjustable half clamp on the side
Indicators/operating means			Other suitable accessories can be fou
Operation indicator		LED green: power on	
Function indicator		LED yellow: 1. LED lit constantly: signal > 2 x switching point (function reserve) 2. LED flashes: signal between 1 x switching point and 2 x switching point 3. LED off: signal < switching point	www.pepperl-fuchs.com
Electrical specifications			
Operating voltage	U _B	12 30 V DC	
No-load supply current	I ₀	Emitter: ≤ 18 mA	
	Ū	Receiver: ≤ 20 mA	
Output			
Switching type		light on	
Signal output		Relay, 1 alternator	
Switching voltage		max. 30 V DC	
Switching current		max. 1 A	
Switching frequency	f	≤ 20 Hz	
Response time	1	≤ 25 ms	
•		S 20 1115	
Conformity			
Product standard		EN 60947-5-2	
Ambient conditions			
Ambient temperature		-25 55 °C (-13 131 °F)	
Storage temperature		-40 70 °C (-40 158 °F)	
Mechanical specifications			
Housing width		18 mm	
Housing height		62 mm	
Housing depth		35 mm	
Degree of protection		IP67	
Connection		Emitter: 0.5 m , 2-wire	
Connection		Receiver: 0.5 m , 5-wire	
Material			
Housing		Polycarbonate	
Optical face		PMMA	
Mass		Emitter: 80 g Receiver: 100 g	
Approvals and certificates			
Protection class		II , rated voltage \leq 250 V AC with pollution degree 1-2 according to IEC 60664-1 Output circuit basis insulation of input circuit according to EN 50178, rated insulation voltage 240 V AC	
UL approval		cULus Listed, Class 2 Power Source, Type 1 enclosure	
CCC approval		CCC approval / marking not required for products rated \leq 36 V	

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group

www.pepperl-fuchs.com

2

> USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

EPPERL+FUCHS

Curves/Diagrams





Release date: 2020-01-20 03:05 Date of issue: 2020-01-20 271173_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group USA: +1 330 486 0001 www.pepperl-fuchs.com