

BNS 260-11/01Z-L



- Long life
- Small body
- Pre-wired cable
- no mechanical wear
- 26 mm x 36 mm x 13 mm
- Insensitive to soiling
- Thermoplastic enclosure
- Concealed mounting possible
- Insensitive to transverse misalignment

Data

Ordering data

BNS 260-11/01Z-L

101184388

EAN (European Article Number) 4030661321882

eCl@ss number, Version 9.0 27-27-24-02

Approval - Standards

TÜV

cULus

EAC

General data

BNS 260

IEC 60947-5-3

BG-GS-ET-14

Installation conditions
(mechanical)

quasi-flush

Enclosure material

Glass-fibre, reinforced thermoplastic

Gross weight

55 g

General data - Features

Coding

Yes

Number of openers

2

Number of shutters

1

Number of safety contacts	2
Number of cable wires	6

Safety appraisal

	ISO 13849-1
Mission Time	20 Year(s)

Safety appraisal - Safety outputs

B10d- Value Normally-closed
 contact/Normally open contact 25,000,000 Operations
 (NC/NO)

Mechanical data

Actuating element	Magnet
Door hinge	Left
Ensured switch distance "ON" S	5 mm
ao	
Ensured switch distance "OFF" S	15 mm
ar	
Notice (Switch distance S _n)	Axial misalignment, a horizontal and vertical misalignment of the safety sensor and the actuator are tolerated. The possible misalignment depends on the distance of the active surfaces of the sensor and the actuator. The sensor remains active within the tolerance range.
Direction of motion	Head-on to the active surface

Mechanical data - Connection technique

Terminal Connector	Cable
Length of cable	1 m
Wire cross-section	0.3 mm ²
	PVC

Mechanical data - Dimensions

Height of sensor	36 mm
Length of sensor	13 mm
Width of sensor	26 mm

Ambient conditions

	IP67
Ambient temperature, minimum	-25 °C
Ambient temperature, maximum	+70 °C
Storage and transport temperature, minimum	-25 °C

Storage and transport temperature, maximum	+70 °C
Resistance to vibrations to EN 60068-2-6	10 ... 55 Hz, amplitude 1 mm 30 g / 11 ms

Electrical data

Voltage type	DC (direct current)
Switching voltage, maximum	75 VDC
Switching current, maximum	0.4 A
Switching capacity, maximum	10 VA
Switching frequency, maximum	5 Hz

Scope of delivery

Included in delivery	Actuators must be ordered separately.
----------------------	---------------------------------------

Accessory

BPS 260
SRB-E-301ST
SRB-E-201LC

Notes

Note (General)	Contact symbols shown for the closed condition of the guard device. The contact configuration for versions with or without LED is identical.
----------------	---

Ordering code

Product type description:

BNS 260-(1)(2)Z(3)-(4)-(5)

(1)

11 1 NO contacts/1 NC contact

02 2 NC contact

(2)

without with diagnostic output

/01 1 NC contact

(3)

without without LED switching conditions display

G with LED switching conditions display

(4)

without Pre-wired cable
ST with connector

- (5)
L Door hinge on left-hand side
R Door hinge on right-hand side


Pictures

Photo/Product/Catalogue




ID: kbns2f07
| 23,0 kB | .png | 74.083 x 49.389 mm - 210 x 140
Pixel - 72 dpi
| 291,7 kB | .jpg | 352.778 x 234.95 mm - 1000 x 666
Pixel - 72 dpi

Dimension/Product/Basic




ID: 1bns2g08
| 6,8 kB | .png | 74.083 x 51.858 mm - 210 x 147 Pixel
- 72 dpi
| 36,4 kB | .cdr |
| 76,0 kB | .jpg | 352.778 x 247.297 mm - 1000 x 701
Pixel - 72 dpi

Graphic/Product/Contact



ID: kbns2k26
| 79,8 kB | .jpg | 352.778 x 99.483 mm - 1000 x 282
Pixel - 72 dpi

Diagramm/Product/Curve



ID: kbns2d03

| 200,1 kB | .jpg | 352.778 x 233.892 mm - 1000 x 663


Pixel - 72 dpi

| 18,5 kB | .png | 74.083 x 49.036 mm - 210 x 139

Pixel - 72 dpi

| 36,8 kB | .cdr |

Diagramm/Product/Curve



ID: kbns2d02

| 200,9 kB | .jpg | 352.778 x 235.303 mm - 1000 x 667


Pixel - 72 dpi

| 19,2 kB | .png | 74.083 x 49.389 mm - 210 x 140

Pixel - 72 dpi

| 36,3 kB | .cdr |

Graphic/Clipart



ID: kbns2c02

| 19,6 kB | .cdr |

| 1,8 kB | .png | 74.083 x 52.211 mm - 210 x 148 Pixel
- 72 dpi

K.A. Schmersal GmbH & Co. KG, Möddinghofe 3, D-42279 Wuppertal

The details and data referred to have been carefully checked. Images may diverge from original. Further technical data can be found in the manual. Technical amendments and errors possible.

Generated on 062021-01-31T06:43:06+01:000601Europe/BerlinSun, 31 Jan 2021 06:43:06

+010006amSunday.31am31Europe/BerlinCET4301Europe/BerlinJanuary2021Sun, 31 Jan 2021 06:43:06

+010001am31