

Model Number

NRB20-L3-E2-IO-V1

Features

- 20 mm flush ٠
- Reduction factor = 1
- Magnetic field resistant
- IO-link interface for service and process data
- Switch point mode or window mode can be set
- Switching function, stability alarm and pulse extension can be set
- 4-way LED indicator
- Quick mounting bracket

Description

Reduction factor 1 sensors reliably detect different metals with the same switch state. The integrated IO-Link interface enables clear identification of the sensor and diagnosis of the sensor condition. When using the sensor, parameters and operating modes can be optimally configured specifically for the intended application. In addition to setting the switching function and a pulse extension, the user can select either switch point mode or window mode in combination with a stability alarm. In switch point mode, the stability alarm signals the detection of an object in the area between the assured operating distance and operating distance $\boldsymbol{s}_n.$ In window mode, it signals the detection of an object below the window between operating distance s_n and the nearest operating distance. A stability alarm is displayed to the user via a flashing LED and process data.

Accessories IO-Link-Master02-USB

IO-Link master, supply via USB port or separate power supply, LED indicators, M12 plug for sensor connection V1-G Female connector, M12, 4-pin, field attachable V1-W Female connector, M12, 4-pin, field attachable V1-G-2M-PVC Female cordset, M12, 4-pin, PVC cable V1-W-2M-PVC Female cordset, M12, 4-pin, PVC cable MHW 01 Modular mounting bracket MH 02-L Mounting aid MH 04-2681F Mounting aid for VariKont, +U1+ and +U9*

Output type				
Rated operating distance	s _n			
Near operating distance				
Installation				
Output polarity				
Assured operating distance	sa			
Reduction factor rAI	u			
Reduction factor r _{Cu}				
Reduction factor r ₃₀₄				
Reduction factor r _{St37}				
Output type				
Nominal ratings				
Operating voltage	UB			
Switching frequency	f			
Switching nequency	'			
Hysteresis	н			
Reverse polarity protection	п			
Short-circuit protection				
Voltage drop	Ud			
Operating current Off-state current	IL .			
	l _r			
No-load supply current	I ₀			
Time delay before availability	t _v B			
Constant magnetic field	B			
Alternating magnetic field	Б			
Operating voltage indicator				
Status indicator				
Functional safety related parameters				
MTTFd				
Mission Time (T _M)				
Diagnostic Coverage (DC)				
Interface				
Interface type				
Transfer rate				
IO-Link Revision				
Min. cycle time				
Process data witdh				
SIO mode support				
Device ID				
Compatible master port type				
Ambient conditions				
Ambient temperature				
Storage temperature				
Mechanical specifications				
Connection type				
Connection type				

Technical Data General specifications Switching function

- Housing material
- Sensing face Degree of protection Mass
- Factory settings Default setting

Compliance with standards and directives Standard conformity

Standards

CCC approval

Approvals and certificates

Protection class Rated insulation voltage U Uim Rated impulse withstand voltage UL approval

Normally open/closed (NO/NC) programmable
PNP
20 mm (factory setting)
15 mm (can be activated by software)
flush DC
0 16.2 mm
1
1
1
1
3-wire
10 30 V DC
0 440 Hz (switch point mode)
0 10 Hz (window mode, switch point mode with stability alarm)
typ. 3 %
reverse polarity protected
pulsing
≤ 0.5 V
0200 mA
0 0.5 mA typ. 60 μA at 25 °C < 20 mA
< 150 ms
200 mT
200 mT
LED, green
LED, yellow
701 a
20 a
0 %

NRB20-L3-E2-IO-V1

IO-Link (via C/Q = pin 4) COM 2 (38.4 kBaud) 1.1 2.3 ms Process data input (control system side): 2 Bit Process data output (control system side): none

0x201001 (2101249)

-25 ... 70 °C (-13 ... 158 °F) -40 ... 85 °C (-40 ... 185 °F)

Connector plug M12 x 1 , 4-pin GD-ZnAl4Cu1, coated mounting flange PA6-GF35 PA 6 Grivory GVN-35H IP67 205 g

operating mode = switch point mode with stability alarm switching function = Normally open (NO) switching distance = 20 mm

EN 60947-5-2:2007 EN 60947-5-2/A1:2012 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012

Ш 60 V 800 V cULus Listed, General Purpose Class 2 power source

CCC approval / marking not required for products rated ≤36 V

306534-0003 2019-06-05 issue: Date of date: 2019-06-05 09:47 Release

ena.xml

Pepperl+Fuchs Group www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

NRB20-L3-E2-IO-V1

Dimensions



Electrical Connection



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)

Switching output modes

Switch point mode at rated operating distance sn

Switch point 2 SP 2 (rated operating distance sn)



Switch point mode with near operating distance

Switch point 1 SP1 (near operating distance)



Window mode

Switch point 2 SP 2 (rated operating distance $s_{n)}$



Stability alarm

Switch point mode with stability alarm (factory default)

Switch point 2 SP 2 (rated operating distance sn)



Window mode with stability alarm

Switch point 2 SP 2 (rated operating distance sn)



Release date: 2019-06-05 09:47 Date of issue: 2019-06-05 306534-0003_eng.xml

3