Retroreflective sensor with polarization filter

RL28-55-LAS/47/82b/105

c (U) us CE VISCO





Model Number

RL28-55-LAS/47/82b/105

Retroreflective sensor with 5-pin, M12 x 1 plastic connector

Features

- Visible red light, pulsed LASER light ٠
- Ultra bright LEDs for power on, weak ٠ signal indication and switching state
- Not sensitive to ambient light, even • with switched energy saving lamps
- Protection class II
- Waterproof, degree of protection IP67 •

Electrical connection



= Dark on

Pinout







Indicators/operating means



Pepperl+Fuchs Group

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" USA: +1 330 486 0001 www.pepperl-fuchs.com

fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



Effective detection range Reflector distance Threshold detection range Reference target Light source Light type Polarization filter Laser nominal ratings Note Laser class Wave length Beam divergence Pulse length Repetition rate max. pulse energy Diameter of the light spot Angle of divergence Ambient light limit Functional safety related parame MTTFd Mission Time (T_M) Diagnostic Coverage (DC) Indicators/operating means Operation indicator

Function indicator

Control elements

Electrical specifications

Operating voltage		
Ripple		
No-load supply current		
Protection class		
Output		
Pre-fault indication output		
Switching type		
Signal output		
Switching voltage		
Switching current		
Voltage drop		
Switching frequency		
Response time		
Conformity		
Product standard		
Laser safety		
Ambient conditions		
Ambient temperature		
Storage temperature		
Mechanical specifications		
1.1		

Housing width Housing height Housing depth Degree of protection Connection Material Housing Optical face Mass

Approvals and certificates

Protection class

UL approval FDA approval

	0 30 m
	0.3 30 m
	42 m
	MH82 reflector
	laser diode
	modulated visible red light
	yes
	LASER LIGHT , DO NOT STARE INTO BEAM
	650 nm
	< 1.5 mrad
	approx. 4.5 µs
	approx. 6 kHz 20 kHz
	4 nJ
	approx. 45 mm at 30 m
	Emitter: < 0.1 ° Receiver: < 2 °
	50000 Lux
eters	
	560 a
	20 a
	0 %
	LED green
	2 LEDs yellow, light up when light beam is free, flash when falling short of the stability control, off when light beam is interrupted
	sensitivity adjustment (Adjustment to < 25% of the effective operating range) , Light-on/dark-on changeover switch
UB	10 30 V DC
	max. 10 %
I ₀	\leq 35 mA
	II, rated insulation voltage \leq 250 V AC with pollution degree 1-2 according to IEC 60664-1
	1 PNP, inactive when falling short of the stability control for 10;s immediately inactive if 4 light beam interruptions take place
	light/dark on switchable
	2 PNP, complementary, short-circuit protected, reverse polarity protected , open collectors
	max. 30 V DC
	max. 200 mA
U _d	≤ 2.5 V DC
f	1000 Hz
	0.5 ms
	EN 60947-5-2
	EN 60825-1
	-10 50 °C (14 122 °F)
	-20 75 °C (-4 167 °F)

25.8 mm 88 mm 54.3 mm **IP67** 5-pin, M12 x 1 plastic connector

Plastic ABS Plastic pane 80 g

> II, rated voltage \leq 250 V AC with pollution degree 1-2 according to IEC 60664-1 E87056, cULus Listed, class 2 power supply, type rating 1 IEC 60825-1:2007 Complies with 21 CFR 1040.10 and

> 1040.11 except for deviations pursuant to Laser Notice No. 50, dated June 24, 2007

Accessories

OMH-05

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

OMH-07

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

OMH-21 Mounting bracket

OMH-22 Mounting bracket

OMH-MLV11-K dove tail mounting clamp

OMH-RLK29-HW Mounting bracket for rear wall mounting

OMH-RL28-C Weld slag cover model

REF-MH82

Reflector with Micro-structure, rectangular 82 mm x 60 mm, mounting holes

Other suitable accessories can be found at www.pepperl-fuchs.com

fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



2



Curves/Diagrams



Laser notice laser class 1

- The irradiation can lead to irritation especially in a dark environment. Do not point at people!
- ٠ Maintenance and repairs should only be carried out by authorized service personnel!
- Attach the device so that the warning is clearly visible and readable.
- Caution Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation • exposure.

www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

