Safety thru-beam sensor







Electrical connection

Design with terminal compartment

Receiver:



Features

Model Number SLA29/35/116 R=65m

with terminal compartment

- ٠ Sensing range up to 65 m
- Self-monitoring (type 4 according to ٠ IEC/EN 61496-1)
- ٠ Red transmission light
- Integrated alignment aid •
- Clearly visible LED functional display ٠ and pre-fault indicator on the receiver
- Sturdy housing .
- Waterproof, degree of protection • IP67
- Operation on control units of SB4 ٠ (SafeBox)

Accessories

OMH-05

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

OMH-21

Mounting bracket

OMH-22 Mounting bracket

OMH-MLV11-K dove tail mounting clamp

MS SLP/SLA28 Fixing plate

MS SLPCM Mounting bracket

SLA-1-M

www.pepperl-fuchs.com

Additional accessories can be found in the Internet.

Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group USA: +1 330 486 0001

fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

EPPPERL+FUCHS



Technical data	
System components	
Emitter	SLA29-T/35/116 R=65M
Receiver	SLA29-R/35/116 R=65M
General specifications	
Effective detection range	6 65 m
Threshold detection range	85 m
Light source	LED
Light type	modulated visible red light
Target size	static: 30 mm dynamic: 40 mm (at $v = 1.6$ m/s of the obstacle)
Alignment aid	LED red in receiver
Angle of divergence	< 5 °
Functional safety related parameters	
Safety Integrity Level (SIL)	SIL 3
Performance level (PL)	PLe
Category	Cat. 4
Mission Time (T _M)	20 a
PFH _d	4.4 E-10
Туре	4
Indicators/operating means	
Operation indicator	LED green
Function indicator	LED yellow: 1. LED lit constantly: signal > 2 x switching point (function reserve) 2. LED flashes: signal between 1 x switching point and 2 x switching point 3. LED off: signal < switching point
Electrical specifications	
Operating voltage U _B	Power supply via control unit
Conformity	
Functional safety	ISO 13849-1
Product standard	EN 61496-1 ; IEC 61496-2
Ambient conditions	
Ambient temperature	-20 60 °C (-4 140 °F)
Storage temperature	-20 70 °C (-4 158 °F)
Relative humidity	max. 95 %, not condensing
Mechanical specifications	
Degree of protection	IP67 according to EN 60529
Connection	terminal compartment
Material	
Housing	ABS plastic, RLA 1021 (yellow) painted
Optical face	Plastic pane
Mass	per device 70 g
Approvals and certificates	
CE conformity	CE
CCC approval	CCC approval / marking not required for products rated ≤36 V
Approvals	TÜV

Curves/Diagrams









Additional information

For much easier alignment even for lond distance applications, an additional red LED is located in the receivers optics:

- · LED constantly illuminated: signal strength < switching level
- · LED flashes: signal strength is between 1-fold switching level and 2-fold switching level
- · LED off:
 - signal strength \geq 2-fold switching level (function reserve)

System accessories

Control units

SC4-2 SB4 (SafeBox)

Cable sockets

Option /73c:

straight:	V1-G-2M-PVC
-	V1-G-5M-PVC
	V1-G-10M-PVC
angled:	V1-W-2M-PVC
	V1-W-5M-PVC
	V1-W-10M-PVC

Option /105:

www.pepperl-fuchs.com

118442_eng.xml



Option /116: no

Mounting aids

OMH-21 OMH-22 OMH-05 OMH-MLV11-K

Further accessories

Laser alignment aid BA SLA28

Muting Set MS SLP/SLA28

Redirection mirror SLA-1-M

