High-Performance Distance Sensor

X1TA101MHV80

Part Number





LASER

• Analog output (0...10 V/4...20 mA)

- **Emitted light disengageable** •
- Graphical display for easy operation
- Temperature drift eliminable

These sensors have scratch-resistant optics and the emitted light can be switched off. They use the transit time measurement principle to measure the distance between the sensor and the object. Using a suitable reflector at the object, a highly accurate position measurement at large distances is also possible.

The configurations are selected using a menu and can be protected by a password.



Technical Data

Optical Data				
Working Range	0,2100,2 m			
Measuring Range				
Reference Reflector/Reflector Foil	4 × RQ100BA			
Resolution	4 × RQ100BA 420 mm			
Linearity	0,05 %			
,				
Switching Hysteresis	1350 mm			
Light Source	Laser (red)			
Wavelength	660 nm			
Service Life $(T = +25 °C)$	100000 h			
Laser Class (EN 60825-1)	1			
Max. Ambient Light	10000 Lux			
Beam Divergence	< 2 mrad			
Light Spot Diameter	see Table 1			
Reflector required	yes			
Electrical Data				
Supply Voltage	1830 V DC			
Current Consumption (Ub = 24 V)	< 100 mA			
Switching Frequency	50 Hz			
Measuring Rate	1100 /s			
On-/Off-Delay	010000 ms			
Temperature Drift	0,5 mm/K			
Temperature Range	-2560 °C			
Number of Switching Outputs	2			
Switching Output Voltage Drop	< 2,5 V			
Switching Output/Switching Current	/Switching Current 200 mA			
Analog Output	010 V/420 mA			
Short Circuit Protection	yes			
Reverse Polarity and Overload Protection	yes			
Protection Class	n Class III			
FDA Accession Number	0920382-000			
Mechanical Data				
Setting Method	Menu (OLED)			
Housing Material	Plastic			
Degree of Protection	IP68			
Connection	M12 × 1; 8-pin			
Safety-relevant Data				
MTTFd (EN ISO 13849-1)	345,65 a			
Error Output	•			
Configurable as PNP/NPN/Push-Pull	Ŏ			
Analog Output	Ū.			
Connection Diagram No.	514			
Control Panel No.	TA1			
Suitable Connection Equipment No.	80			
Suitable Mounting Technology No.	340			

Display brightness may decrease with age. This does not result in any impairment of the sensor function.

Complementary Products

Analog Evaluation Unit AW02 Reflector, Reflector Foil Set Protective Housing ZST-NN-02

Photoelectronic Sensors





Ctrl. Panel		
TA1		
60		
21 = Mode Button 60 = Display		

54.4	
All dimensions in mm (1 mm = 0.03	9
Screw M4 = $0,5$ Nm	



Legen	d		PT	Platinum measuring resistor	ENARS422	Encoder A/Ā (TTL)
+	Supply Voltage +		nc	not connected	ENBR5422	Encoder B/B (TTL)
-	Supply Voltage 0 V		U	Test Input	ENA	Encoder A
~	Supply Voltage (AC Voltage)		Ū	Test Input inverted	ENв	Encoder B
А	Switching Output	(NO)	W	Trigger Input	Amin	Digital output MIN
Ā	Switching Output	(NC)	W -	Ground for the Trigger Input	Амах	Digital output MAX
V	Contamination/Error Output	(NO)	0	Analog Output	Аок	Digital output OK
V	Contamination/Error Output	(NC)	0-	Ground for the Analog Output	SY In	Synchronization In
E	Input (analog or digital)		BZ	Block Discharge	SY OUT	Synchronization OUT
т	Teach Input		Awv	Valve Output	OLT	Brightness output
Z	Time Delay (activation)		а	Valve Control Output +	м	Maintenance
S	Shielding		b	Valve Control Output 0 V	rsv	reserved
RxD	Interface Receive Path		SY	Synchronization	Wire Co	lors according to DIN IEC 757
TxD	Interface Send Path		SY-	Ground for the Synchronization	BK	Black
RDY	Ready		E+	Receiver-Line	BN	Brown
GND	Ground		S+	Emitter-Line	RD	Red
CL	Clock		÷	Grounding	OG	Orange
E/A	Output/Input programmable		SnR	Switching Distance Reduction	YE	Yellow
0	IO-Link		Rx+/-	Ethernet Receive Path	GN	Green
PoE	Power over Ethernet		Tx+/-	Ethernet Send Path	BU	Blue
IN	Safety Input		Bus	Interfaces-Bus A(+)/B(-)	VT	Violet
OSSD	Safety Output		La	Emitted Light disengageable	GY	Grey
Signal	Signal Output		Mag	Magnet activation	WH	White
BI_D+/-	Ethernet Gigabit bidirect. data	line (A-D)	RES	Input confirmation	PK	Pink
EN0 RS42	Encoder 0-pulse 0-0 (TTL)		EDM	Contactor Monitoring	GNYE	Green/Yellow

Table 1

Working Distance	0 m	40 m	100 m
Light Spot Diameter	5 mm	80 mm	< 200 mm

Feasible reflector distance

Reflector type, mounting distance

RQ100BA	5100 m	ZRAF07K01	0,240 m			
RF505	0,240 m	ZRAF08K01	0,240 m			
RF508	0,240 m	ZRDF03K01	0,240 m			
RF258	0,240 m	ZRDF10K01	0,2100 m			



