### **HRTL 8**

MMM

2 kHz

(HF)-

A<sup>2</sup>LS

Push-pull switching outputs

• Laser-generated red light, laser class 2 Adjustable background suppression • A<sup>2</sup>LS - Active Ambient Light Suppression

• M12 turning connector or cable connection

... 400mm

5

en 09-2014/09 50116483-02

10 - 30 V

### Laser diffuse reflection light scanner with background suppression

### **Dimensioned drawing**









- Α В Transmitter
- С Optical axis
- D Operational control
- Е Yellow LED
- Turning connector, 90° F

## **Electrical connection**









### **Accessories:**

(available separately)

- M12 connectors (KD ...)
- Ready-made cables (K-D ...)
- Mounting systems
- Control guard •

# ▲ Leuze electronic

## **HRTL 8**

#### Tables



Typ. scanning range limit [mm]

### Diagrams



# Remarks

 Install sensor inclined at angle of approx. 10° if used to detect objects with shiny surfaces.

### **Specifications**

#### **Optical data**

Typ. scanning range limit (white 90%) 1) Scanning range<sup>2)</sup> Mechanical adjustment range Light beam characteristic Beam spread Light source Wavelength Max. output power Pulse duration Timing Switching frequency Response time Delay before start-up Electrical data Operating voltage U<sub>B</sub><sup>3)</sup> Residual ripple Open-circuit current Signal voltage high/low .../24 Switching output/function .../66 Output current Scanning range adjustment Indicators Yellow LED Mechanical data Housing Optics cover Weight (plug/cable) Connection type **Environmental data** Ambient temp. (operation/storage) Protective circuit <sup>5)</sup>

VDE safety class 6) Protection class 7) Laser class Standards applied Certifications

- IP 69K test acc. to DIN 40050 part 9 simulated, high pressure cleaning conditions without the use of additives, 8)
- 9) These proximity switches shall be used with UL Listed Cable assemblies rated 30V, 0.5A min,

#### Operate in accordance with intended use!

b This product is not a safety sensor and is not intended as personnel protection.

by The product may only be put into operation by competent persons.

Solve the product in accordance with the intended use

### Order guide

	Designation	Part No.
With M12 connector	HRTL 8/24-350-S12	50036370
With 2m cable	HRTL 8/24-350	50036371
With M12 connector	HRTL 8/66-350-S12	50102705
With 5m cable	HRTL 8/66-350, 5000	50103709

#### 70g/140g M12 connector, 5-pin or cable: 2000mm, 5x0.25mm<sup>2</sup> -10°C ... +40°C/-40°C ... +70°C 2, 3 II, all-insulated IP 67, IP 69K <sup>8)</sup> 2 (acc. to EN 60825-1) IEC 60947-5-2 UL 508, C22.2 No.14-13 3) 9)

 $\leq$  3511A  $\geq$  (U<sub>B</sub>-2V)/ $\leq$  2V PNP and NPN transistor output, light switching 2 push-pull switching outputs <sup>4)</sup> pin 2: PNP dark switching, NPN light switching pin 4: PNP light switching, NPN dark switching

mechanical via multiturn potentiometer

Laser class 2

5 ... 400mm

50 ... 400mm

655nm (visible red light)

see tables

focussed

laser

3mW

≤8µs

2000Hz

0.25ms

≤ 100ms

≤ 35 mA

10 ... 30VDC

 $\leq$  15% of U<sub>B</sub>

max. 100mA

object detected

metal

glass

 $\geq 0.5 \, mrad$ 

1) Typ. scanning range limit: max. attainable range without performance reserve

- 2) Scanning range: recommended range with performance reserve
- 3) For UL applications: for use in class 2 circuits according to NEC only
- 4) The push-pull switching outputs must not be connected in parallel
- 2=polarity reversal protection, 3=short-circuit protection for all outputs 5)

Rating voltage 250VAC 6)

In stop position of the turning connector (turning connector locked) 7)

acids and bases are not part of the test

in the field installation, or equivalent (categories: CYJV/CYJV7 or PVVA/PVVA7)

### HRTL 8 Laser diffuse reflection light scanner with background suppression

### Laser safety notices

#### ATTENTION, LASER RADIATION – LASER CLASS 2

#### Never look directly into the beam!

The device fulfills the EN 60825-1:2008-05 (IEC 60825-1:2007) safety regulations for a product in **laser class 2** as well as the U.S. 21 CFR 1040.10 regulations with deviations corresponding to "Laser Notice No. 50" from June 24th, 2007.

- ♥ Never look directly into the laser beam or in the direction of reflecting laser beams!
- If you look into the beam path over a longer time period, there is a risk of injury to the retina.
- ✤ Do not point the laser beam of the device at persons!
- the laser beam with an opaque, non-reflective object if the laser beam is accidentally directed towards a person.
- ♦ When mounting and aligning the device, avoid reflections of the laser beam off reflective surfaces!
- CAUTION! Use of controls or adjustments or performance of procedures other than specified herein may result in hazardous light exposure.
  - The use of optical instruments or devices (e.g., magnifying glasses, binoculars) with the product will increase eye hazard.
- Adhere to the applicable legal and local regulations regarding protection from laser beams acc. to EN 60825 (IEC 60825) in its latest version.
- The device must not be tampered with and must not be changed in any way. There are no user-serviceable parts inside the device.
  Repairs must only be performed by Leuze electronic GmbH + Co. KG.

#### NOTICE

#### Affix laser information and warning signs!

Laser information and warning signs are affixed to the device(see ①). In addition, self-adhesive laser information and warning signs (stick-on labels) are supplied in several languages (see ②).

- Affix the laser information sheet with the language appropriate for the place of use to the device.
- When using the device in the US, use the stick-on label with the "Complies with 21 CFR 1040.10" notice.
- Affix the laser information and warning signs near the device if no signs are attached to the device (e.g. because the device is too small) or if the attached laser information and warning signs are concealed due to the installation position. Affix the laser information and warning signs so that they are legible without exposing the reader to the laser radiation of the device or other optical radiation.



# ▲ Leuze electronic

HRTL 8