







RL28-55-Z/82b/110/112

Retroreflective sensor with metal connector M12; 5-pin, 90° convertible

Features

- ٠ Ultra bright LEDs for power on, weak signal indication and switching state
- Programmable time function GAN, • GAB, IAB and GAN-IAB as double function
- ٠ Not sensitive to ambient light, even with switched energy saving lamps
- Waterproof, degree of protection IP67 ٠
- Protection class II

ON OFF Time adjuster for Off delay and one delay DIP-switch Time adjuste for On delay 3 Internal connection Internal connection

DIP-switch

Dimensions



Electrical connection









1	BIN	(browr
2	WH	(white)
3	BU	(blue)
4	BK	(black)
5	GY	(gray)

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



Technical data

General specifications		
Effective detection range		0 17 m
Reflector distance		0.05 17 m
Threshold detection range		21 m
Reference target		H85-2 reflector
Light source		LED
Light type		modulated visible red light , 660 nm
Polarization filter		yes
Diameter of the light spot		approx. 290 mm at a distance of 17 m
Angle of divergence		emitter 1.2° receiver 2°
Ambient light limit		80000 Lux
Functional safety related paran	neters	
MTTF _d		690 a
Mission Time (T _M)		20 a
Diagnostic Coverage (DC)		0 %
Indicators/operating means		
Operation indicator		LED green
Function indicator		2 LEDs yellow, light up when light beam is free, flash when falling short of the stability control, off when light beam is interrupted
Control elements		sensitivity adjustment (Adjustment to < 25% of the effective operating range), Light-on/dark-on changeover switch
Electrical specifications		
Operating voltage	UB	10 30 V DC
Ripple		10 %
No-load supply current	I ₀	40 mA
Output		
Pre-fault indication output		1 PNP, inactive when falling short of the stability control for 10;s immediately inactive if 4 light beam interruptions take place
Switching type		light/dark on, switchable . (selectable, light/dark switching is only activated if the receiver has 'dark on' selected.)
Signal output		1 push-pull (4 in 1) output, short-circuit protected, reverse polarity protected
Switching voltage		max. 30 V DC
Switching current		max. 100 mA
Switching frequency	f	1000 Hz
Response time		0.5 ms
Timer function		ON delay (GAN), OFF delay (GAB), one shot (IAB), ON delay- one shot (GAN-IAB), ON delay-OFF delay (GAN-GAB), programmable adjustment interval 0.02 s 1 s
Conformity		
Product standard		EN 60947-5-2
Ambient conditions		
Ambient temperature		-40 60 °C (-40 140 °F)
Storage temperature		-40 75 °C (-40 167 °F)
Mechanical specifications		
Housing width		25.8 mm
Housing height		88 mm
Housing depth		65.5 mm
Degree of protection		IP67
Connection		5-pin, M12 x 1 connector, 90° rotatable
Material		
Housing		Plastic ABS
Optical face		plastic
Connector		metal
Mass		approx. 100 g
Approvals and certificates		
UL approval		E87056 , $cULus$ Listed , class 2 power supply , type rating 1

Accessories

OMH-05

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

OMH-07

Mounting aid for round steel ø 12 mm or sheet 1.5 mm ... 3 mm

OMH-21 Mounting bracket

OMH-22

Mounting bracket OMH-MLV11-K

OMH-RLK29-HW

dove tail mounting clamp

Mounting bracket for rear wall mounting OMH-RL28-C

Weld slag cover model

Other suitable accessories can be found at www.pepperl-fuchs.com



2

Curves/Diagrams





Timer functions

Timer function	Switching type		Receiver exposed Receiver dark
ON ON Without	Light Dark		ON OFF
	Light		ON OFF ON
ON LE CON delay	Dark		OFF ON
	Light		OFF ON
ON OFF delay	Dark		OFF ON
ON 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	Light	tos tos	OFF ON
one shot	Dark	tos tos	OFF

Time $t_{ON},\,t_{OFF}$ and t_{OS} are adjustable from 0.02 to 1 seconds. The Light-/Dark-Switch (Left, outer switch) is shown in the "Dark ON" position.

Туре	Description	Notes
-Z	OFF delay timer	Adjustable time interval
	one shot timer	(0.02 s - 1 s)
	ON delay timer	
	ON delay timer / OFF delay timer	
	ON delay timer / one shot timer	

