Reflex Sensor with Background Suppression

OHII102C0203

Part Number



- Hygienic design makes it easy to clean
- Made with food safe materials that are FDA approved
- Touch teach-in, external teach-in
- Waterproof (IP68/IP69K)

InoxSens is the hygiene series from wenglor. The innovative design of InoxSens sensors allows contamination and cleaning agents to flow off by themselves. A variety of components form a complete system which integrates seamlessly into the machine. The laser welded stainless steel housing made of V4A (1.4404/316L) is corrosion-free and resistant to cleaning agents. Gapfree mounting with InoxLock and the captive optics further contribute to these sensors' optimal suitability for cleaning-heavy environments. The InoxSens sensors are set up with the help of touch teach-in and is made possible by the hermetically sealed housing.



Technical Data

Optical Data	
Range	100 mm
Adjustable Range	10100 mm
Switching Hysteresis	< 5 %
Light Source	Red Light
Service Life (T = +25 °C)	100000 h
Max. Ambient Light	10000 Lux
Light Spot Diameter	see Table 1
Electrical Data	
Supply Voltage	1030 V
Current Consumption (Ub = 24 V)	< 30 mA
Switching Frequency	600 Hz
Response Time	800 µs
Temperature Drift	< 10 %
Temperature Range	-2560 °C
Switching Output Voltage Drop	< 2,5 V
PNP Switching Output/Switching Current	200 mA
Short Circuit Protection	yes
Reverse Polarity Protection	yes
Overload Protection	yes
Lockable	yes
Teach Mode	HT, VT
Protection Class	,
Mechanical Data	
Setting Method	Teach-In
Housing Material	Stainless Steel 316L
Degree of Protection	IP68/IP69K
Connection	M12 × 1; 4-pin
Optic Cover	Glass
Material Control Panel	PC (FDA)
Ecolab	yes
PNP NO/NC switchable	
RS-232 with Adapterbox	Ŏ
Connection Diagram No.	152
Control Panel No.	li1
Suitable Connection Equipment No.	2
Suitable Mounting Technology No.	140 490

Complementary Products

Adapterbox A232 PNP-NPN Converter BG2V1P-N-2M Software

Photoelectronic Sensors

InoxSens







- 1 = Emitter
- 2 = Receiver
- All dimensions in mm (1 mm = 0.03937 Inch)



Legen	d		PT	Platinum measuring resistor	ENARS422	Encoder A/Ā (TTL)
+	Supply Voltage +		nc	not connected	ENBR5422	Encoder B/B (TTL)
-	Supply Voltage 0 V		U	Test Input	ENa	Encoder A
~	Supply Voltage (AC Voltage)		Ū	Test Input inverted	ENв	Encoder B
А	Switching Output	(NO)	W	Trigger Input	Amin	Digital output MIN
Ā	Switching Output	(NC)	W -	Ground for the Trigger Input	Амах	Digital output MAX
V	Contamination/Error Output	(NO)	0	Analog Output	Аок	Digital output OK
V	Contamination/Error Output	(NC)	0-	Ground for the Analog Output	SY In	Synchronization In
Е	Input (analog or digital)		BZ	Block Discharge	SY OUT	Synchronization OUT
Т	Teach Input		Awv	Valve Output	OLT	Brightness output
Z	Time Delay (activation)		a	Valve Control Output +	м	Maintenance
S	Shielding		b	Valve Control Output 0 V	rsv	reserved
RxD	Interface Receive Path		SY	Synchronization	Wire Co	lors according to DIN IEC 757
TxD	Interface Send Path		SY-	Ground for the Synchronization	BK	Black
RDY	Ready		E+	Receiver-Line	BN	Brown
GND	Ground		S+	Emitter-Line	RD	Red
CL	Clock		÷	Grounding	OG	Orange
E/A	Output/Input programmable		SnR	Switching Distance Reduction		Yellow
۲	IO-Link		Rx+/-	Ethernet Receive Path	GN	Green
PoE	Power over Ethernet		Tx+/-	Ethernet Send Path	BU	Blue
IN	Safety Input		Bus	Interfaces-Bus A(+)/B(-)	VT	Violet
OSSD	Safety Output		La	Emitted Light disengageable	GY	Grey
Signal			Mag	Magnet activation	WH	White
	Ethernet Gigabit bidirect. data	line (A-D)	RES	Input confirmation	PK	Pink
ENO RS42	Encoder 0-pulse 0-0 (TTL)		EDM	Contactor Monitoring	GNYE	Green/Yellow

Table 1

Detection Range	10 mm	40 mm	100 mm
Light Spot Diameter	2,5 × 7 mm	2,5 × 5 mm	2,5 × 2,5 mm

Switching Distance Deviation

Typical characteristic curve based on white, 90 % remission





dSr = Switching Distance Change