Dimensions



Model Number

convertible

Features

٠

•

•

٠

٠

•

Retroreflective sensor

standard housing

sizes > 0.3 mm

tal housing frame

thanks to small light spot

ration under all conditions

MLV12-54-LAS-300/76b/110/124

with metal connector M12; 5-pin, 90°

Series of sensors in a widely used

Visible red light, pulsed LASER light

Precision: high degree of repeatability

Reliable detection of minimum target

Resistant against noise: reliable ope-

High level of stability thanks to the me-



Electrical connection



- = Dark on
- **Pinout**



Indicators/operating means



Refer to "General Notes Relating to Pepperl+Fuchs Product Information" Pepperl+Fuchs Group www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com



	Accessories
	OMH-MLV12-HWG
100 450 mm	Mounting bracket for series MLV12 sen-
0.02 4 m	sors
5.6 m	
MH82 reflector	OMH-MLV12-HWK
laser diode	Mounting bracket for series MLV12 sen-
modulated visible red light	sors
LASER LIGHT , DO NOT STARE INTO BEAM	ОМН-К01
650 nm	dove tail mounting clamp
2 mrad	OMH-K02
1.8 µs	dove tail mounting clamp
17.86 kHz	
1.1 nJ	ОМН-К03
> 0.3 mm	dove tail mounting clamp
approx. 0.5 mm at detection range 150 mm up to 400 mm	ОМН-01
0.1 °	Mounting aid for round steel ø 12 mm or
	sheet 1.5 mm 3 mm
50000 Lux	SHEEL 1.3 HIII 3 HIIII
5000 Lux	ОМН-06
	Mounting aid for round steel ø 12 mm or
930 a	sheet 1.5 mm 3 mm
10 a	
0 %	REF-MH82
	Reflector with Micro-structure, rectangu-
LED green, flashes in case of short-circuit	lar 82 mm x 60 mm, mounting holes
2 LEDs yellow, light up when light beam is free, flash when falling short of the stability control, off when light beam is interrupted	
rotary switch for light/dark, sensitivity adjuster	REF-MH50
Totaly switch for light dark, sensitivity adjuster	Reflector with Micro-structure, rectangu-
10 30 V DC	lar 50.9 mm x 50.9 mm, mounting holes,
max. 10 %	fixing strap
max. 40 mA	REF-MH78
	Reflector with Micro-structure, hexagonal
emitter deactivation at 0 V	78 mm x 61 mm, mounting holes
light/dark on switchable	REF-MH20
1 push-pull (4 in 1) output, short-circuit protected, reverse pola-	Reflector with Micro-structure, rectangu-
rity protected	lar 32 mm x 20 mm, mounting holes
max. 30 V DC	REF-MA21
max. 0.1 A	Reflector with Micro-structure, round ø 21
≤ 2.5 V DC 2500 Hz	mm, self-adhesive
0.2 ms	
0.2 113	OFR-MCS-A4
-10 50 °C (14 122 °F)	Reflective tape A4 (297 mm x 210 mm)
-20 65 °C (-4 149 °F)	
	OFR-MCS-400/18
IP67	Reflective tape, cut to size
Metal connector, M12, 5-pin, 90° rotatable	Other suitable accessories can be found at
	www.pepperl-fuchs.com
Frame: nickel plated, die cast zinc,	
Laterals: glass-fiber reinforced plastic PC	, and the second s
Plastic pane	ີ ອີນເ
60 g	05
	128105_eng.xm
EN 60947-5-2:2007	5-11
IEC 60947-5-2:2007	13-0
IEC / EN 60068. half-sine, 40 g in each X, Y and Z directions	. 20
IEC / EN 60068-2-6. Sinus. 10 -150 Hz, 5 g in each X, Y and Z	enss
directions	Date of issue: 2013-05-13
IEC 60825-1:2007 Complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated	Cate
June 24, 2007	
	16:41
	18 18
II, rated voltage ≤ 300 V AC with pollution degree 1-2 accor-	ase date: 2013-04-18 16:45
ding to IEC 60664-1	2013
cULus Listed, Type 1 enclosure	tte: 5
CCC approval / marking not required for products rated \leq 36 V	e da
	a N

Technical data General specifications Effective detection range 100 ... 450 mm 0.02 ... 4 m Reflector distance Threshold detection range 5.6 m MH82 reflector Reference target Light source laser diode Light type modulated visible red light Laser nominal ratings LASER LIGHT, DO NOT STARE INTO BE Note Laser class 650 nm Wave length Beam divergence 2 mrad Pulse length 1.8 μs Repetition rate 17.86 kHz max. pulse energy 1.1 nJ Target size > 0.3 mm Diameter of the light spot approx. 0.5 mm at detection range 150 mr 0.1 Angle of divergence Ambient light limit 50000 Lux Continuous light Modulated light 5000 Lux Functional safety related parameters $\mathsf{MTTF}_{\mathsf{d}}$ 930 a Mission Time (T_M) 10 a Diagnostic Coverage (DC) 0 % Indicators/operating means Operating display LED green, flashes in case of short-circuit Function display 2 LEDs yellow, light up when light beam is short of the stability control, off when light rotary switch for light/dark, sensitivity adjust Controls **Electrical specifications** Operating voltage UB 10 ... 30 V DC max. 10 % Ripple No-load supply current max. 40 mA I_0 Input Test input emitter deactivation at 0 V Output Switching type light/dark on switchable 1 push-pull (4 in 1) output, short-circuit pro Signal output rity protected Switching voltage max. 30 V DC Switching current max. 0.1 A \leq 2.5 V DC Voltage drop Ud Switching frequency 2500 Hz Response time 0.2 ms Ambient conditions Ambient temperature -10 ... 50 °C (14 ... 122 °F) Storage temperature -20 ... 65 °C (-4 ... 149 °F) **Mechanical specifications** Protection degree **IP67** Connection Metal connector, M12, 5-pin, 90° rotatable Material Housing Frame: nickel plated, die cast zinc, Laterals: glass-fiber reinforced plastic PC Optical face Plastic pane Mass 60 g Compliance with standards and directives Standard conformity Product standard EN 60947-5-2:2007 IEC 60947-5-2:2007 Shock and impact resistance IEC / EN 60068. half-sine, 40 g in each X, Vibration resistance IEC / EN 60068-2-6. Sinus. 10 -150 Hz, 5 directions Laser class IEC 60825-1:2007 Complies with 21 CFR except for deviations pursuant to Laser No June 24, 2007 Approvals and certificates

Protection class UL approval

Pepperl+Fuchs Group

www.pepperl-fuchs.com

CCC approval

2

fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

Release date: 2013-04-18 16:45



Curves/Diagrams



Laser notice laser class 1

- The irradiation can lead to irritation especially in a dark environment. Do not point at people!
- Maintenance and repairs should only be carried out by authorized service personnel!
- Attach the device so that the warning is clearly visible and readable.
- The warning accompanies the device and should be attached in immediate proximity to the device.
- Caution Use of controls or adjustments or performance of procedures other than those specified herein may result in hazard-٠ ous radiation exposure.

